

F1.E.201-15D

| CFM | Static Pressure in Inches W.G. | | | | | | | | | | | | |
|------|--------------------------------|-------------|-------------|-------------|-------------|-------------|-------------|-------------|-------------|-------------|-------------|-------------|-------------|
| | 0.000 | 0.250 | 0.500 | 0.750 | 1.000 | 1.250 | 1.500 | 1.750 | 2.000 | 2.250 | 2.500 | 2.750 | 3.000 |
| | RPM/BHP | RPM/BHP | RPM/BHP | RPM/BHP | RPM/BHP | RPM/BHP | RPM/BHP | RPM/BHP | RPM/BHP | RPM/BHP | RPM/BHP | RPM/BHP | RPM/BHP |
| 800 | | 935 / 0.13 | 1146 / 0.22 | 1320 / 0.33 | 1471 / 0.44 | 1603 / 0.56 | 1724 / 0.69 | 1839 / 0.82 | 1942 / 0.95 | 2041 / 1.09 | 2139 / 1.24 | 2228 / 1.39 | 2312 / 1.55 |
| 1200 | 999 / 0.17 | 1193 / 0.28 | 1362 / 0.40 | 1515 / 0.53 | 1655 / 0.68 | 1780 / 0.83 | 1896 / 0.99 | 2007 / 1.16 | 2109 / 1.33 | 2206 / 1.50 | 2294 / 1.67 | 2381 / 1.85 | 2469 / 2.04 |
| 1600 | 1332 / 0.40 | 1484 / 0.55 | 1621 / 0.70 | 1749 / 0.85 | 1869 / 1.02 | 1985 / 1.20 | 2092 / 1.39 | 2195 / 1.58 | 2292 / 1.79 | 2385 / 1.99 | 2473 / 2.20 | 2556 / 2.41 | 2640 / 2.64 |
| 2000 | 1665 / 0.77 | 1789 / 0.97 | 1903 / 1.15 | 2012 / 1.34 | 2116 / 1.53 | 2217 / 1.73 | 2315 / 1.95 | 2407 / 2.16 | 2497 / 2.39 | 2584 / 2.62 | 2667 / 2.86 | | |
| 2400 | 1998 / 1.34 | 2103 / 1.58 | 2202 / 1.80 | 2297 / 2.03 | 2386 / 2.24 | 2474 / 2.47 | 2561 / 2.71 | 2643 / 2.94 | | | | | |
| 2800 | 2331 / 2.12 | 2422 / 2.41 | 2509 / 2.68 | 2590 / 2.93 | | | | | | | | | |

Max Sizeable RPM = 3000 RPM. Table shown extended beyond this point for reference only.

- Motor .5018OT3E56-S48PP has an rpm range of 800 to 1730.
- Motor .5018OT3E56-S48PP-50HZ has an rpm range of 800 to 1400.
- Motor .7518OT3E56-S48PP has an rpm range of 800 to 1735.
- Motor .7518OT3E56-S48PP-50Hz has an rpm range of 800 to 1410.
- Motor 00118ET3H143T-W22 has an rpm range of 800 to 1750.
- Motor 00118OT3H143T-S has an rpm range of 800 to 1750.
- Motor 00158ET3H145T-W22 has an rpm range of 800 to 1750.
- Motor 00158OT3H145T-S has an rpm range of 800 to 1750.
- Motor 00218ET3H145T-W22 has an rpm range of 800 to 1750.
- Motor 00218OT3H145T-S has an rpm range of 800 to 1750.
- Motor 00336OT3H145T-S has an rpm range of 900 to 3000.
- Motor BMN145-2.0I2-CS-UB1-50 (1200RPM) has an rpm range of 800 to 1200.
- Motor BMN145-2.0I2-CS-UB1-60 (1200RPM) has an rpm range of 800 to 1200.
- Motor BMN145-2.0I2-ES-UB1-50 (1800RPM) has an rpm range of 800 to 1800.
- Motor BMN145-2.0I2-ES-UB1-60 (1800RPM) has an rpm range of 800 to 1800.
- Motor BMN48-750I1-E-50-115 has an rpm range of 800 to 1800.
- Motor BMN48-750I1-E-60-115 has an rpm range of 800 to 1800.
- Motor BMN48-750I2-E-50-230/277 has an rpm range of 800 to 1800.
- Motor BMN48-750I2-E-60-230/277 has an rpm range of 800 to 1800.
- Motor DTP0014 has an rpm range of 800 to 1750.
- Motor DTP0014-50HZ has an rpm range of 800 to 1429.
- Motor DTP0016 has an rpm range of 800 to 1150.
- Motor DTP0022 has an rpm range of 900 to 3000.
- Motor DTP0022-50 has an rpm range of 900 to 3000.
- Motor DTP0024 has an rpm range of 800 to 1740.
- Motor DTP0024-50HZ has an rpm range of 800 to 1415.
- Motor DTP0032 has an rpm range of 900 to 3000.
- Motor DTP1/54 has an rpm range of 800 to 1750.
- Motor DTP1/54-50HZ has an rpm range of 800 to 1426.
- Motor GP0014 has an rpm range of 800 to 1800.
- Motor GP0014-50 has an rpm range of 800 to 1440.
- Motor GP0024 has an rpm range of 800 to 1740.
- Motor GP0024-50 has an rpm range of 800 to 1440.
- Motor GP1/54 has an rpm range of 800 to 1800.
- Motor GP1/54-50 has an rpm range of 800 to 1440.
- Motor NP0024 has an rpm range of 800 to 1740.
- Motor NP1/54 has an rpm range of 800 to 1730.