

F2-E.735-20D

CFM	Static Pressure in Inches W.G.								
	0.000	0.500	1.000	1.500	2.000	2.500	3.000	3.500	4.000
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
2000		898 / 0.41	1109 / 0.73	1287 / 1.10	1444 / 1.53	1586 / 1.99	1714 / 2.47	1833 / 2.98	1944 / 3.49
2500		1008 / 0.60	1203 / 0.96	1367 / 1.36	1514 / 1.81	1650 / 2.31	1776 / 2.84	1893 / 3.41	2002 / 3.99
3000	889 / 0.42	1126 / 0.84	1307 / 1.27	1461 / 1.72	1598 / 2.19	1726 / 2.71	1845 / 3.27	1958 / 3.87	2063 / 4.49
3500	1037 / 0.66	1248 / 1.16	1418 / 1.66	1562 / 2.16	1693 / 2.68	1813 / 3.23	1927 / 3.82	2035 / 4.44	2137 / 5.09
4000	1184 / 0.99	1374 / 1.55	1534 / 2.12	1672 / 2.69	1796 / 3.27	1910 / 3.86	2018 / 4.48	2120 / 5.13	2219 / 5.81
4500	1333 / 1.40	1504 / 2.03	1654 / 2.68	1785 / 3.32	1904 / 3.96	2013 / 4.61	2117 / 5.28	2213 / 5.96	2308 / 6.67
5000	1481 / 1.93	1636 / 2.61	1777 / 3.34	1903 / 4.06	2016 / 4.77	2122 / 5.49	2221 / 6.21	2315 / 6.94	
5500	1629 / 2.56	1771 / 3.30	1903 / 4.11	2023 / 4.91	2133 / 5.70	2234 / 6.48	2330 / 7.26		
6000	1777 / 3.33	1907 / 4.13	2032 / 5.00	2146 / 5.88	2251 / 6.74				
6500	1925 / 4.23	2045 / 5.09	2162 / 6.03	2269 / 6.96					

Max Sizeable RPM = 2400 RPM. Table shown extended beyond this point for reference only.

- Motor 00212ET3E184T-W22 has an rpm range of 800 to 1150.
- Motor 00212ET3H184T-W22 has an rpm range of 800 to 1150.
- Motor 00212OT3H184T-S has an rpm range of 800 to 1150.
- Motor 00218ET3H145T-W22 has an rpm range of 800 to 1750.
- Motor 00218OT3H145T-S has an rpm range of 800 to 1750.
- Motor 00318ET3H182T-W22 has an rpm range of 800 to 1750.
- Motor 00318OT3H182T-S has an rpm range of 800 to 1750.
- Motor 00518ET3H184T-W22 has an rpm range of 800 to 1750.
- Motor 00518OT3H184T-S has an rpm range of 800 to 1750.
- Motor 00718OT3H213T-S has an rpm range of 800 to 1750.
- Motor BMN145-2.0I2-CS-UB1-50 (1200RPM) has an rpm range of 800 to 1200.
- Motor BMN145-2.0I2-CS-UB1-60 (1200RPM) has an rpm range of 800 to 1200.
- Motor BMN145-2.0I2-ES-UB1-50 (1800RPM) has an rpm range of 800 to 1800.
- Motor BMN145-2.0I2-ES-UB1-60 (1800RPM) has an rpm range of 800 to 1800.
- Motor DHP0026 has an rpm range of 800 to 1150.
- Motor DTP0024 has an rpm range of 800 to 1740.
- Motor DTP0024-50HZ has an rpm range of 800 to 1415.
- Motor DTP0026 has an rpm range of 800 to 1150.
- Motor DTP0026-50 has an rpm range of 800 to 958.
- Motor DTP0034 has an rpm range of 800 to 1755.
- Motor DTP0034-50HZ has an rpm range of 800 to 1438.
- Motor DTP0036 has an rpm range of 800 to 1150.
- Motor DTP0054 has an rpm range of 800 to 1750.
- Motor DTP0054-50 has an rpm range of 800 to 1435.
- Motor DTP0056 has an rpm range of 800 to 1150.
- Motor DTP7/54 has an rpm range of 800 to 1750.
- Motor DTP7/54-50 has an rpm range of 800 to 1470.
- Motor EP0026 has an rpm range of 800 to 1150.
- Motor GP0024 has an rpm range of 800 to 1740.
- Motor GP0024-50 has an rpm range of 800 to 1440.
- Motor GP0026 has an rpm range of 800 to 1150.
- Motor GP0034 has an rpm range of 800 to 1800.
- Motor GP0034-50 has an rpm range of 800 to 1440.
- Motor GP0054 has an rpm range of 800 to 1800.
- Motor GP0054-50 has an rpm range of 800 to 1440.
- Motor NP0024 has an rpm range of 800 to 1740.
- Motor NP0026 has an rpm range of 800 to 1150.
- Motor NP0034 has an rpm range of 800 to 1755.
- Motor NP0054 has an rpm range of 800 to 1745.