

INSA20D

CFM	Static Pressure in Inches W.G.								
	0.000	0.500	1.000	1.500	2.000	2.500	3.000	3.500	4.000
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
1500		814 / 0.29	1047 / 0.59	1238 / 0.94	1399 / 1.32	1538 / 1.71			
1750		867 / 0.36	1084 / 0.66	1270 / 1.04	1431 / 1.46	1574 / 1.90	1701 / 2.35	1815 / 2.79	1919 / 3.22
2000		924 / 0.44	1129 / 0.76	1305 / 1.15	1463 / 1.59	1605 / 2.06	1735 / 2.56	1852 / 3.07	1961 / 3.58
2250		984 / 0.54	1178 / 0.88	1346 / 1.27	1498 / 1.73	1638 / 2.23	1766 / 2.76	1884 / 3.31	1995 / 3.88
2500		1046 / 0.66	1232 / 1.02	1391 / 1.43	1538 / 1.89	1673 / 2.41	1799 / 2.95	1917 / 3.54	2028 / 4.15
2750	875 / 0.40	1110 / 0.80	1288 / 1.19	1441 / 1.61	1581 / 2.09	1711 / 2.60	1835 / 3.17	1950 / 3.78	2058 / 4.40
3000	955 / 0.52	1176 / 0.95	1347 / 1.38	1495 / 1.83	1628 / 2.30	1754 / 2.84	1873 / 3.41	1985 / 4.02	2094 / 4.68
3250	1034 / 0.66	1240 / 1.12	1408 / 1.59	1551 / 2.07	1680 / 2.56	1801 / 3.10	1915 / 3.69	2025 / 4.31	2130 / 4.97
3500	1114 / 0.82	1309 / 1.33	1470 / 1.83	1608 / 2.33	1734 / 2.85	1851 / 3.41	1961 / 4.00	2067 / 4.63	2169 / 5.30
3750	1193 / 1.01	1378 / 1.55	1534 / 2.09	1668 / 2.63	1790 / 3.18	1903 / 3.75	2010 / 4.35	2113 / 4.99	2211 / 5.67
4000	1273 / 1.23	1448 / 1.80	1599 / 2.38	1729 / 2.95	1848 / 3.53	1957 / 4.12	2062 / 4.75	2161 / 5.40	2257 / 6.09

Max Sizeable RPM = 2400 RPM. Table shown extended beyond this point for reference only.

- Motor 00212ET3E184T-W22 has an rpm range of 800 to 1150.
- Motor 00212ET3H184T-W22 has an rpm range of 800 to 1150.
- Motor 00212OT3H184T-S has an rpm range of 800 to 1150.
- Motor 00218ET3H145T-W22 has an rpm range of 800 to 1750.
- Motor 00218OT3H145T-S has an rpm range of 800 to 1750.
- Motor 00318ET3H182T-W22 has an rpm range of 800 to 1750.
- Motor 00318OT3H182T-S has an rpm range of 800 to 1750.
- Motor 00518ET3H184T-W22 has an rpm range of 800 to 1750.
- Motor 00518OT3H184T-S has an rpm range of 800 to 1750.
- Motor 00718OT3H213T-S has an rpm range of 800 to 1750.
- Motor BMN145-2.0I2-CS-UB1-50 (1200RPM) has an rpm range of 800 to 1200.
- Motor BMN145-2.0I2-CS-UB1-60 (1200RPM) has an rpm range of 800 to 1200.
- Motor BMN145-2.0I2-ES-UB1-50 (1800RPM) has an rpm range of 800 to 1800.
- Motor BMN145-2.0I2-ES-UB1-60 (1800RPM) has an rpm range of 800 to 1800.
- Motor DHP0026 has an rpm range of 800 to 1150.
- Motor DTP0024 has an rpm range of 800 to 1740.
- Motor DTP0024-50HZ has an rpm range of 800 to 1415.
- Motor DTP0026 has an rpm range of 800 to 1150.
- Motor DTP0026-50 has an rpm range of 800 to 958.
- Motor DTP0034 has an rpm range of 800 to 1755.
- Motor DTP0034-50HZ has an rpm range of 800 to 1438.
- Motor DTP0036 has an rpm range of 800 to 1150.
- Motor DTP0054 has an rpm range of 800 to 1750.
- Motor DTP0054-50 has an rpm range of 800 to 1435.
- Motor DTP0056 has an rpm range of 800 to 1150.
- Motor DTP7/54 has an rpm range of 800 to 1750.
- Motor DTP7/54-50 has an rpm range of 800 to 1470.
- Motor EP0026 has an rpm range of 800 to 1150.
- Motor GP0024 has an rpm range of 800 to 1740.
- Motor GP0024-50 has an rpm range of 800 to 1440.
- Motor GP0026 has an rpm range of 800 to 1150.
- Motor GP0034 has an rpm range of 800 to 1800.
- Motor GP0034-50 has an rpm range of 800 to 1440.
- Motor GP0054 has an rpm range of 800 to 1800.
- Motor GP0054-50 has an rpm range of 800 to 1440.
- Motor NP0024 has an rpm range of 800 to 1740.
- Motor NP0026 has an rpm range of 800 to 1150.
- Motor NP0034 has an rpm range of 800 to 1755.
- Motor NP0054 has an rpm range of 800 to 1745.