

SA20D

CFM	Static Pressure in Inches W.G.								
	0.000	0.500	1.000	1.500	2.000	2.500	3.000	3.500	4.000
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
1500			1021 / 0.54	1212 / 0.88	1374 / 1.25	1518 / 1.64	1645 / 2.03		
2000		875 / 0.38	1092 / 0.70	1271 / 1.06	1429 / 1.48	1571 / 1.93	1699 / 2.41	1820 / 2.91	1931 / 3.42
2500		975 / 0.54	1176 / 0.91	1346 / 1.31	1494 / 1.75	1631 / 2.23	1757 / 2.76	1873 / 3.30	1983 / 3.87
3000	823 / 0.33	1082 / 0.75	1271 / 1.18	1430 / 1.62	1572 / 2.10	1702 / 2.61	1821 / 3.16	1935 / 3.74	2042 / 4.35
3500	960 / 0.52	1193 / 1.01	1372 / 1.51	1523 / 2.01	1658 / 2.53	1781 / 3.08	1897 / 3.66	2006 / 4.27	2108 / 4.90
4000	1097 / 0.78	1308 / 1.33	1477 / 1.91	1621 / 2.48	1751 / 3.05	1869 / 3.64	1977 / 4.24	2084 / 4.90	2183 / 5.57
4500	1235 / 1.11	1425 / 1.72	1586 / 2.38	1725 / 3.02	1849 / 3.66	1962 / 4.30	2069 / 4.96	2170 / 5.65	2266 / 6.35
5000	1371 / 1.52	1546 / 2.19	1698 / 2.92	1831 / 3.64	1951 / 4.35	2061 / 5.06	2164 / 5.78	2260 / 6.50	2353 / 7.25
5500	1509 / 2.03	1669 / 2.75	1813 / 3.55	1940 / 4.35	2056 / 5.14	2162 / 5.91	2262 / 6.69	2356 / 7.49	
6000	1646 / 2.63	1793 / 3.41	1929 / 4.28	2052 / 5.15	2164 / 6.02	2267 / 6.87			

Max Sizeable RPM = 2400 RPM. Table shown extended beyond this point for reference only.

- Motor 00152ET3E182T-W22 has an rpm range of 800 to 1150.
- Motor 00212ET3E184T-W22 has an rpm range of 800 to 1150.
- Motor 00212ET3H184T-W22 has an rpm range of 800 to 1150.
- Motor 00212OT3H184T-S has an rpm range of 800 to 1150.
- Motor 00218ET3H145T-W22 has an rpm range of 800 to 1750.
- Motor 00218OT3H145T-S has an rpm range of 800 to 1750.
- Motor 00318ET3H182T-W22 has an rpm range of 800 to 1750.
- Motor 00318OT3H182T-S has an rpm range of 800 to 1750.
- Motor 00518ET3H184T-W22 has an rpm range of 800 to 1750.
- Motor 00518OT3H184T-S has an rpm range of 800 to 1750.
- Motor 00718OT3H213T-S has an rpm range of 800 to 1750.
- Motor BMN145-2.0I2-CS-UB1-50 (1200RPM) has an rpm range of 800 to 1200.
- Motor BMN145-2.0I2-CS-UB1-60 (1200RPM) has an rpm range of 800 to 1200.
- Motor BMN145-2.0I2-ES-UB1-50 (1800RPM) has an rpm range of 800 to 1800.
- Motor BMN145-2.0I2-ES-UB1-60 (1800RPM) has an rpm range of 800 to 1800.
- Motor DHP0026 has an rpm range of 800 to 1150.
- Motor DTP0016 has an rpm range of 800 to 1150.
- Motor DTP0024 has an rpm range of 800 to 1740.
- Motor DTP0024-50HZ has an rpm range of 800 to 1415.
- Motor DTP0026 has an rpm range of 800 to 1150.
- Motor DTP0026-50 has an rpm range of 800 to 958.
- Motor DTP0034 has an rpm range of 800 to 1755.
- Motor DTP0034-50HZ has an rpm range of 800 to 1438.
- Motor DTP0036 has an rpm range of 800 to 1150.
- Motor DTP0054 has an rpm range of 800 to 1750.
- Motor DTP0054-50 has an rpm range of 800 to 1435.
- Motor DTP0056 has an rpm range of 800 to 1150.
- Motor DTP1/54 has an rpm range of 800 to 1750.
- Motor DTP1/56 has an rpm range of 800 to 1150.
- Motor DTP1/56-50 has an rpm range of 800 to 958.
- Motor DTP7/54 has an rpm range of 800 to 1750.
- Motor DTP7/54-50 has an rpm range of 800 to 1470.
- Motor EP0026 has an rpm range of 800 to 1150.
- Motor GP0024 has an rpm range of 800 to 1740.
- Motor GP0024-50 has an rpm range of 800 to 1440.
- Motor GP0026 has an rpm range of 800 to 1150.
- Motor GP0034 has an rpm range of 800 to 1800.
- Motor GP0034-50 has an rpm range of 800 to 1440.
- Motor GP0054 has an rpm range of 800 to 1800.
- Motor GP0054-50 has an rpm range of 800 to 1440.
- Motor GP1/54 has an rpm range of 800 to 1800.
- Motor GP1/56 has an rpm range of 800 to 1150.
- Motor NP0024 has an rpm range of 800 to 1740.
- Motor NP0026 has an rpm range of 800 to 1150.
- Motor NP0034 has an rpm range of 800 to 1755.
- Motor NP0054 has an rpm range of 800 to 1745.

Motor NP1/54 has an rpm range of 800 to 1730.