

# F1-E.354-15D

CFM	Static Pressure in Inches W.G.												
	0.000	0.250	0.500	0.750	1.000	1.250	1.500	1.750	2.000	2.250	2.500	2.750	3.000
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
800		935 / 0.13	1146 / 0.22	1320 / 0.33	1471 / 0.44	1603 / 0.56	1724 / 0.69	1839 / 0.82	1942 / 0.95	2041 / 1.09	2139 / 1.24	2228 / 1.39	2312 / 1.55
1200	999 / 0.17	1193 / 0.28	1362 / 0.40	1515 / 0.53	1655 / 0.68	1780 / 0.83	1896 / 0.99	2007 / 1.16	2109 / 1.33	2206 / 1.50	2294 / 1.67	2381 / 1.85	2469 / 2.04
1600	1332 / 0.40	1484 / 0.55	1621 / 0.70	1749 / 0.85	1869 / 1.02	1985 / 1.20	2092 / 1.39	2195 / 1.58	2292 / 1.79	2385 / 1.99	2473 / 2.20	2556 / 2.41	2640 / 2.64
2000	1665 / 0.77	1789 / 0.97	1903 / 1.15	2012 / 1.34	2116 / 1.53	2217 / 1.73	2315 / 1.95	2407 / 2.16	2497 / 2.39	2584 / 2.62	2667 / 2.86		
2400	1998 / 1.34	2103 / 1.58	2202 / 1.80	2297 / 2.03	2386 / 2.24	2474 / 2.47	2561 / 2.71	2643 / 2.94					
2800	2331 / 2.12	2422 / 2.41	2509 / 2.68	2590 / 2.93									

Max Sizeable RPM = 3000 RPM. Table shown extended beyond this point for reference only.

- Motor .5018OT3E56-S48PP has an rpm range of 800 to 1730.
- Motor .5018OT3E56-S48PP-50HZ has an rpm range of 800 to 1400.
- Motor .7518OT3E56-S48PP has an rpm range of 800 to 1735.
- Motor .7518OT3E56-S48PP-50Hz has an rpm range of 800 to 1410.
- Motor 00118ET3H143T-W22 has an rpm range of 800 to 1750.
- Motor 00118OT3H143T-S has an rpm range of 800 to 1750.
- Motor 00158ET3H145T-W22 has an rpm range of 800 to 1750.
- Motor 00158OT3H145T-S has an rpm range of 800 to 1750.
- Motor 00218ET3H145T-W22 has an rpm range of 800 to 1750.
- Motor 00218OT3H145T-S has an rpm range of 800 to 1750.
- Motor 00336OT3H145T-S has an rpm range of 900 to 3000.
- Motor BMN145-2.0I2-CS-UB1-50 (1200RPM) has an rpm range of 800 to 1200.
- Motor BMN145-2.0I2-CS-UB1-60 (1200RPM) has an rpm range of 800 to 1200.
- Motor BMN145-2.0I2-ES-UB1-50 (1800RPM) has an rpm range of 800 to 1800.
- Motor BMN145-2.0I2-ES-UB1-60 (1800RPM) has an rpm range of 800 to 1800.
- Motor BMN48-750I1-E-50-115 has an rpm range of 800 to 1800.
- Motor BMN48-750I1-E-60-115 has an rpm range of 800 to 1800.
- Motor BMN48-750I2-E-50-230/277 has an rpm range of 800 to 1800.
- Motor BMN48-750I2-E-60-230/277 has an rpm range of 800 to 1800.
- Motor DTP0014 has an rpm range of 800 to 1750.
- Motor DTP0014-50HZ has an rpm range of 800 to 1429.
- Motor DTP0016 has an rpm range of 800 to 1150.
- Motor DTP0022 has an rpm range of 900 to 3000.
- Motor DTP0022-50 has an rpm range of 900 to 3000.
- Motor DTP0024 has an rpm range of 800 to 1740.
- Motor DTP0024-50HZ has an rpm range of 800 to 1415.
- Motor DTP0032 has an rpm range of 900 to 3000.
- Motor DTP1/54 has an rpm range of 800 to 1750.
- Motor DTP1/54-50HZ has an rpm range of 800 to 1426.
- Motor GP0014 has an rpm range of 800 to 1800.
- Motor GP0014-50 has an rpm range of 800 to 1440.
- Motor GP0024 has an rpm range of 800 to 1740.
- Motor GP0024-50 has an rpm range of 800 to 1440.
- Motor GP1/54 has an rpm range of 800 to 1800.
- Motor GP1/54-50 has an rpm range of 800 to 1440.
- Motor NP0024 has an rpm range of 800 to 1740.
- Motor NP1/54 has an rpm range of 800 to 1730.