

F1.E.202-18Z

| CFM | Static Pressure in Inches W.G. | | | | | | | | | | | | | | | |
|------|--------------------------------|-------------|-------------|-------------|-------------|-------------|-------------|-------------|-------------|-------------|-------------|-------------|-------------|-------------|-------------|-------------|
| | 0.000 | 0.250 | 0.500 | 0.750 | 1.000 | 1.250 | 1.500 | 1.750 | 2.000 | 2.250 | 2.500 | 2.750 | 3.000 | 3.250 | 3.500 | 3.750 |
| | RPM/BHP | RPM/BHP | RPM/BHP | RPM/BHP | RPM/BHP | RPM/BHP | RPM/BHP | RPM/BHP | RPM/BHP | RPM/BHP | RPM/BHP | RPM/BHP | RPM/BHP | RPM/BHP | RPM/BHP | RPM/BHP |
| 800 | 576 / 0.04 | 766 / 0.10 | 927 / 0.16 | 1065 / 0.24 | 1189 / 0.32 | 1299 / 0.39 | 1404 / 0.48 | 1498 / 0.56 | 1590 / 0.65 | 1674 / 0.73 | 1754 / 0.82 | 1835 / 0.92 | 1909 / 1.02 | 1980 / 1.12 | 2051 / 1.22 | 2116 / 1.32 |
| 1200 | 863 / 0.14 | 992 / 0.22 | 1118 / 0.31 | 1235 / 0.40 | 1341 / 0.50 | 1439 / 0.61 | 1531 / 0.72 | 1619 / 0.83 | 1702 / 0.95 | 1783 / 1.07 | 1858 / 1.18 | 1932 / 1.30 | 2003 / 1.43 | 2069 / 1.54 | 2135 / 1.67 | 2202 / 1.80 |
| 1600 | 1150 / 0.34 | 1248 / 0.44 | 1347 / 0.55 | 1441 / 0.66 | 1531 / 0.78 | 1618 / 0.91 | 1700 / 1.04 | 1778 / 1.18 | 1854 / 1.32 | 1925 / 1.46 | 1998 / 1.61 | 2065 / 1.76 | 2130 / 1.91 | 2195 / 2.06 | 2257 / 2.21 | 2315 / 2.36 |
| 2000 | 1438 / 0.66 | 1516 / 0.79 | 1595 / 0.92 | 1674 / 1.05 | 1750 / 1.19 | 1825 / 1.34 | 1896 / 1.49 | 1967 / 1.65 | 2035 / 1.81 | 2101 / 1.97 | 2165 / 2.14 | 2227 / 2.31 | 2288 / 2.49 | 2347 / 2.67 | 2404 / 2.84 | 2460 / 3.02 |
| 2400 | 1725 / 1.14 | 1790 / 1.29 | 1856 / 1.45 | 1922 / 1.60 | 1983 / 1.75 | 2051 / 1.93 | 2115 / 2.10 | 2176 / 2.27 | 2237 / 2.45 | 2297 / 2.64 | 2355 / 2.83 | 2412 / 3.02 | 2469 / 3.22 | 2524 / 3.42 | 2575 / 3.61 | 2629 / 3.82 |
| 2800 | 2013 / 1.81 | 2068 / 1.98 | 2124 / 2.16 | 2181 / 2.34 | 2238 / 2.53 | 2293 / 2.72 | 2349 / 2.91 | 2403 / 3.10 | 2458 / 3.30 | 2511 / 3.50 | 2564 / 3.71 | 2617 / 3.93 | 2667 / 4.14 | 2718 / 4.36 | 2767 / 4.58 | 2817 / 4.81 |

Max Sizeable RPM = 2900 RPM. Table shown extended beyond this point for reference only.

Motor 186726/A01-ECM-50-277-18 has an rpm range of 320 to 1950.

Motor 186726/A01-ECM-60-277-18 has an rpm range of 320 to 1950.

Motor 186730/A01-ECM-50-240-18 has an rpm range of 320 to 2700.

Motor 186730/A01-ECM-60-240-18 has an rpm range of 320 to 2700.

Motor 186731/A01-ECM-50-480-18 has an rpm range of 320 to 2900.

Motor 186731/A01-ECM-60-480-18 has an rpm range of 320 to 2900.