

# F1.E.204-15D

CFM	Static Pressure in Inches W.G.												
	0.000	0.250	0.500	0.750	1.000	1.250	1.500	1.750	2.000	2.250	2.500	2.750	3.000
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
800		935 / 0.13	1146 / 0.22	1320 / 0.33	1471 / 0.44	1603 / 0.56	1724 / 0.69	1839 / 0.82	1942 / 0.95	2041 / 1.09	2139 / 1.24	2228 / 1.39	2312 / 1.55
1200	999 / 0.17	1193 / 0.28	1362 / 0.40	1515 / 0.53	1655 / 0.68	1780 / 0.83	1896 / 0.99	2007 / 1.16	2109 / 1.33	2206 / 1.50	2294 / 1.67	2381 / 1.85	2469 / 2.04
1600	1332 / 0.40	1484 / 0.55	1621 / 0.70	1749 / 0.85	1869 / 1.02	1985 / 1.20	2092 / 1.39	2195 / 1.58	2292 / 1.79	2385 / 1.99	2473 / 2.20	2556 / 2.41	2640 / 2.64
2000	1665 / 0.77	1789 / 0.97	1903 / 1.15	2012 / 1.34	2116 / 1.53	2217 / 1.73	2315 / 1.95	2407 / 2.16	2497 / 2.39	2584 / 2.62	2667 / 2.86		
2400	1998 / 1.34	2103 / 1.58	2202 / 1.80	2297 / 2.03	2386 / 2.24	2474 / 2.47	2561 / 2.71	2643 / 2.94					
2800	2331 / 2.12	2422 / 2.41	2509 / 2.68	2590 / 2.93									

Max Sizeable RPM = 3000 RPM. Table shown extended beyond this point for reference only.

Motor .5018OT3E56-S48PP has an rpm range of 800 to 1730.

Motor .5018OT3E56-S48PP-50HZ has an rpm range of 800 to 1400.

Motor .7518OT3E56-S48PP has an rpm range of 800 to 1735.

Motor .7518OT3E56-S48PP-50Hz has an rpm range of 800 to 1410.

Motor 00118ET3H143T-W22 has an rpm range of 800 to 1750.

Motor 00118OT3H143T-S has an rpm range of 800 to 1750.

Motor 00158ET3H145T-W22 has an rpm range of 800 to 1750.

Motor 00158OT3H145T-S has an rpm range of 800 to 1750.

Motor 00218ET3H145T-W22 has an rpm range of 800 to 1750.

Motor 00218OT3H145T-S has an rpm range of 800 to 1750.

Motor 00336OT3H145T-S has an rpm range of 900 to 3000.

Motor BMN145-2.0I2-CS-UB1-50 (1200RPM) has an rpm range of 800 to 1200.

Motor BMN145-2.0I2-CS-UB1-60 (1200RPM) has an rpm range of 800 to 1200.

Motor BMN145-2.0I2-ES-UB1-50 (1800RPM) has an rpm range of 800 to 1800.

Motor BMN145-2.0I2-ES-UB1-60 (1800RPM) has an rpm range of 800 to 1800.

Motor BMN48-750I1-E-50-115 has an rpm range of 800 to 1800.

Motor BMN48-750I1-E-60-115 has an rpm range of 800 to 1800.

Motor BMN48-750I2-E-50-230/277 has an rpm range of 800 to 1800.

Motor BMN48-750I2-E-60-230/277 has an rpm range of 800 to 1800.

Motor DTP0014 has an rpm range of 800 to 1750.

Motor DTP0014-50HZ has an rpm range of 800 to 1429.

Motor DTP0016 has an rpm range of 800 to 1150.

Motor DTP0022 has an rpm range of 900 to 3000.

Motor DTP0022-50 has an rpm range of 900 to 3000.

Motor DTP0024 has an rpm range of 800 to 1740.

Motor DTP0024-50HZ has an rpm range of 800 to 1415.

Motor DTP0032 has an rpm range of 900 to 3000.

Motor DTP1/54 has an rpm range of 800 to 1750.

Motor DTP1/54-50HZ has an rpm range of 800 to 1426.

Motor GP0014 has an rpm range of 800 to 1800.

Motor GP0014-50 has an rpm range of 800 to 1440.

Motor GP0024 has an rpm range of 800 to 1740.

Motor GP0024-50 has an rpm range of 800 to 1440.

Motor GP1/54 has an rpm range of 800 to 1800.

Motor GP1/54-50 has an rpm range of 800 to 1440.

Motor NP0024 has an rpm range of 800 to 1740.

Motor NP1/54 has an rpm range of 800 to 1730.