

F2-E.1195-20Z

| CFM | Static Pressure in Inches W.G. | | | | | | | | | | | | |
|------|--------------------------------|-------------|-------------|-------------|-------------|-------------|-------------|-------------|-------------|-------------|-------------|-------------|-------------|
| | 0.000 | 0.250 | 0.500 | 0.750 | 1.000 | 1.250 | 1.500 | 1.750 | 2.000 | 2.250 | 2.500 | 2.750 | 3.000 |
| | RPM/BHP | RPM/BHP | RPM/BHP | RPM/BHP | RPM/BHP | RPM/BHP | RPM/BHP | RPM/BHP | RPM/BHP | RPM/BHP | RPM/BHP | RPM/BHP | RPM/BHP |
| 2000 | 775 / 0.15 | 877 / 0.24 | 974 / 0.35 | 1063 / 0.47 | 1146 / 0.60 | 1225 / 0.74 | 1301 / 0.88 | 1376 / 1.02 | 1447 / 1.17 | 1517 / 1.33 | 1585 / 1.49 | 1650 / 1.65 | 1715 / 1.82 |
| 2500 | 968 / 0.29 | 1050 / 0.39 | 1132 / 0.53 | 1209 / 0.67 | 1281 / 0.82 | 1351 / 0.98 | 1416 / 1.14 | 1481 / 1.31 | 1543 / 1.47 | 1605 / 1.65 | 1664 / 1.83 | 1723 / 2.01 | 1781 / 2.20 |
| 3000 | 1161 / 0.49 | 1230 / 0.62 | 1299 / 0.77 | 1366 / 0.93 | 1431 / 1.10 | 1492 / 1.28 | 1552 / 1.46 | 1609 / 1.65 | 1665 / 1.84 | 1719 / 2.04 | 1773 / 2.24 | 1826 / 2.44 | 1877 / 2.65 |
| 3500 | 1355 / 0.78 | 1413 / 0.92 | 1472 / 1.09 | 1532 / 1.27 | 1589 / 1.46 | 1645 / 1.66 | 1698 / 1.86 | 1751 / 2.07 | 1802 / 2.29 | 1852 / 2.51 | 1900 / 2.73 | 1948 / 2.95 | 1994 / 3.18 |
| 4000 | 1549 / 1.17 | 1599 / 1.33 | 1652 / 1.51 | 1703 / 1.70 | 1754 / 1.91 | 1804 / 2.13 | 1854 / 2.35 | 1902 / 2.58 | 1948 / 2.82 | 1995 / 3.06 | 2040 / 3.30 | 2083 / 3.55 | 2127 / 3.80 |
| 4500 | 1741 / 1.66 | 1787 / 1.84 | 1833 / 2.04 | 1880 / 2.25 | 1926 / 2.47 | 1971 / 2.71 | 2016 / 2.95 | 2059 / 3.20 | 2103 / 3.45 | 2146 / 3.72 | 2187 / 3.98 | 2228 / 4.25 | 2268 / 4.52 |
| 5000 | 1935 / 2.28 | 1976 / 2.48 | 2017 / 2.69 | 2058 / 2.91 | 2101 / 3.16 | 2142 / 3.41 | 2182 / 3.66 | 2223 / 3.93 | 2263 / 4.21 | | | | |
| 5500 | 2128 / 3.03 | 2165 / 3.25 | 2204 / 3.48 | 2241 / 3.72 | 2278 / 3.97 | | | | | | | | |

Max Sizeable RPM = 2300 RPM. Table shown extended beyond this point for reference only.

Motor 186735/A01-ECM-50-240-20 has an rpm range of 300 to 2300.

Motor 186735/A01-ECM-60-240-20 has an rpm range of 300 to 2300.

Motor 186741/A01-ECM-50-480-20 has an rpm range of 300 to 2300.

Motor 186741/A01-ECM-60-480-20 has an rpm range of 300 to 2300.