

F3-E.1224-24D

CFM	Static Pressure in Inches W.G.														
	0.000	0.250	0.500	0.750	1.000	1.250	1.500	1.750	2.000	2.250	2.500	2.750	3.000	3.250	3.500
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
4000		850 / 1.28	927 / 1.62	996 / 1.95	1059 / 2.29	1118 / 2.64	1173 / 3.00	1225 / 3.36	1275 / 3.73	1322 / 4.11	1368 / 4.50	1412 / 4.90	1455 / 5.30	1495 / 5.71	1536 / 6.13
4500	852 / 1.28	936 / 1.72	1008 / 2.11	1073 / 2.48	1132 / 2.86	1188 / 3.24	1241 / 3.63	1291 / 4.03	1339 / 4.43	1385 / 4.84	1429 / 5.26	1472 / 5.69	1513 / 6.12	1553 / 6.56	1592 / 7.01
5000	946 / 1.75	1024 / 2.25	1091 / 2.69	1152 / 3.11	1208 / 3.53	1261 / 3.95	1312 / 4.37	1360 / 4.80	1406 / 5.24	1450 / 5.68	1493 / 6.14	1534 / 6.59	1574 / 7.06	1613 / 7.53	1651 / 8.00
5500	1041 / 2.33	1112 / 2.88	1175 / 3.38	1233 / 3.85	1287 / 4.31	1337 / 4.77	1385 / 5.23	1431 / 5.70	1476 / 6.17	1518 / 6.64	1559 / 7.13	1599 / 7.62	1638 / 8.12	1676 / 8.61	1713 / 9.13
6000	1136 / 3.03	1202 / 3.64	1261 / 4.19	1316 / 4.71	1366 / 5.21	1415 / 5.71	1461 / 6.22	1505 / 6.72	1548 / 7.23	1589 / 7.74	1629 / 8.26	1667 / 8.78	1705 / 9.31	1742 / 9.84	
6500	1230 / 3.85	1292 / 4.51	1348 / 5.12	1400 / 5.69	1448 / 6.25	1494 / 6.79	1538 / 7.34	1581 / 7.89	1622 / 8.43	1662 / 8.98	1700 / 9.53				
7000	1325 / 4.81	1382 / 5.53	1435 / 6.19	1485 / 6.82	1531 / 7.42	1575 / 8.02	1618 / 8.61	1658 / 9.19	1698 / 9.77						
7500	1419 / 5.92	1473 / 6.69	1524 / 7.41	1571 / 8.09	1615 / 8.75	1657 / 9.39									
8000	1514 / 7.18	1565 / 8.01	1613 / 8.79	1658 / 9.53											

Max Sizeable RPM = 2000 RPM. Table shown extended beyond this point for reference only.

- Motor 00318ET3H182T-W22 has an rpm range of 800 to 1750.
- Motor 00318OT3H182T-S has an rpm range of 800 to 1750.
- Motor 00512ET3E215T-W22 has an rpm range of 800 to 1150.
- Motor 00512OT3H215T-S has an rpm range of 800 to 1150.
- Motor 00518ET3H184T-W22 has an rpm range of 800 to 1750.
- Motor 00518OT3H184T-S has an rpm range of 800 to 1750.
- Motor 00718OT3H213T-S has an rpm range of 800 to 1750.
- Motor 01018OT3H215T-S has an rpm range of 800 to 1750.
- Motor DHP0056 has an rpm range of 800 to 1165.
- Motor DP010504NPW01 has an rpm range of 800 to 1750.
- Motor DTP0026 has an rpm range of 800 to 1150.
- Motor DTP0034 has an rpm range of 800 to 1755.
- Motor DTP0034-50HZ has an rpm range of 800 to 1438.
- Motor DTP0036 has an rpm range of 800 to 1150.
- Motor DTP0054 has an rpm range of 800 to 1750.
- Motor DTP0054-50 has an rpm range of 800 to 1435.
- Motor DTP0056 has an rpm range of 800 to 1150.
- Motor DTP0104 has an rpm range of 800 to 1755.
- Motor DTP0104-50 has an rpm range of 800 to 1436.
- Motor DTP7/54 has an rpm range of 800 to 1750.
- Motor DTP7/54-50 has an rpm range of 800 to 1470.
- Motor GP0034 has an rpm range of 800 to 1800.
- Motor GP0034-50 has an rpm range of 800 to 1440.
- Motor GP0054 has an rpm range of 800 to 1800.
- Motor GP0054-50 has an rpm range of 800 to 1440.
- Motor GP0056 has an rpm range of 800 to 1150.
- Motor GP0104 has an rpm range of 800 to 1755.
- Motor GP0104-50 has an rpm range of 800 to 1440.
- Motor NP0056 has an rpm range of 800 to 1150.