

F3-E.642-24D

CFM	Static Pressure in Inches W.G.														
	0.000	0.250	0.500	0.750	1.000	1.250	1.500	1.750	2.000	2.250	2.500	2.750	3.000	3.250	3.500
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
4000		850 / 1.28	927 / 1.62	996 / 1.95	1059 / 2.29	1118 / 2.64	1173 / 3.00	1225 / 3.36	1275 / 3.73	1322 / 4.11	1368 / 4.50	1412 / 4.90	1455 / 5.30	1495 / 5.71	1536 / 6.13
4500	852 / 1.28	936 / 1.72	1008 / 2.11	1073 / 2.48	1132 / 2.86	1188 / 3.24	1241 / 3.63	1291 / 4.03	1339 / 4.43	1385 / 4.84	1429 / 5.26	1472 / 5.69	1513 / 6.12	1553 / 6.56	1592 / 7.01
5000	946 / 1.75	1024 / 2.25	1091 / 2.69	1152 / 3.11	1208 / 3.53	1261 / 3.95	1312 / 4.37	1360 / 4.80	1406 / 5.24	1450 / 5.68	1493 / 6.14	1534 / 6.59	1574 / 7.06	1613 / 7.53	1651 / 8.00
5500	1041 / 2.33	1112 / 2.88	1175 / 3.38	1233 / 3.85	1287 / 4.31	1337 / 4.77	1385 / 5.23	1431 / 5.70	1476 / 6.17	1518 / 6.64	1559 / 7.13	1599 / 7.62	1638 / 8.12	1676 / 8.61	1713 / 9.13
6000	1136 / 3.03	1202 / 3.64	1261 / 4.19	1316 / 4.71	1366 / 5.21	1415 / 5.71	1461 / 6.22	1505 / 6.72	1548 / 7.23	1589 / 7.74	1629 / 8.26	1667 / 8.78	1705 / 9.31	1742 / 9.84	
6500	1230 / 3.85	1292 / 4.51	1348 / 5.12	1400 / 5.69	1448 / 6.25	1494 / 6.79	1538 / 7.34	1581 / 7.89	1622 / 8.43	1662 / 8.98	1700 / 9.53				
7000	1325 / 4.81	1382 / 5.53	1435 / 6.19	1485 / 6.82	1531 / 7.42	1575 / 8.02	1618 / 8.61	1658 / 9.19	1698 / 9.77						
7500	1419 / 5.92	1473 / 6.69	1524 / 7.41	1571 / 8.09	1615 / 8.75	1657 / 9.39									
8000	1514 / 7.18	1565 / 8.01	1613 / 8.79	1658 / 9.53											

Max Sizeable RPM = 2000 RPM. Table shown extended beyond this point for reference only.

Motor 00318ET3H182T-W22 has an rpm range of 800 to 1750.

Motor 00318OT3H182T-S has an rpm range of 800 to 1750.

Motor 00512ET3E215T-W22 has an rpm range of 800 to 1150.

Motor 00512OT3H215T-S has an rpm range of 800 to 1150.

Motor 00518ET3H184T-W22 has an rpm range of 800 to 1750.

Motor 00518OT3H184T-S has an rpm range of 800 to 1750.

Motor 00718OT3H213T-S has an rpm range of 800 to 1750.

Motor 01018OT3H215T-S has an rpm range of 800 to 1750.

Motor DHP0056 has an rpm range of 800 to 1165.

Motor DP010504NPW01 has an rpm range of 800 to 1750.

Motor DTP0026 has an rpm range of 800 to 1150.

Motor DTP0034 has an rpm range of 800 to 1755.

Motor DTP0034-50HZ has an rpm range of 800 to 1438.

Motor DTP0036 has an rpm range of 800 to 1150.

Motor DTP0054 has an rpm range of 800 to 1750.

Motor DTP0054-50 has an rpm range of 800 to 1435.

Motor DTP0056 has an rpm range of 800 to 1150.

Motor DTP0104 has an rpm range of 800 to 1755.

Motor DTP0104-50 has an rpm range of 800 to 1436.

Motor DTP7/54 has an rpm range of 800 to 1750.

Motor DTP7/54-50 has an rpm range of 800 to 1470.

Motor GP0034 has an rpm range of 800 to 1800.

Motor GP0034-50 has an rpm range of 800 to 1440.

Motor GP0054 has an rpm range of 800 to 1800.

Motor GP0054-50 has an rpm range of 800 to 1440.

Motor GP0056 has an rpm range of 800 to 1150.

Motor GP0104 has an rpm range of 800 to 1755.

Motor GP0104-50 has an rpm range of 800 to 1440.

Motor NP0056 has an rpm range of 800 to 1150.