

# F4-E.1684-28Z

CFM	Static Pressure in Inches W.G.												
	0.000	0.250	0.500	0.750	1.000	1.250	1.500	1.750	2.000	2.250	2.500	2.750	3.000
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
6000	863 / 1.07	904 / 1.35	948 / 1.65	993 / 1.98	1039 / 2.33	1085 / 2.70	1130 / 3.08	1175 / 3.48	1218 / 3.89	1261 / 4.31	1303 / 4.74	1343 / 5.18	1383 / 5.63
6500	935 / 1.36	973 / 1.66	1013 / 1.98	1054 / 2.32	1096 / 2.69	1139 / 3.08	1181 / 3.48	1223 / 3.90	1264 / 4.33	1304 / 4.77	1344 / 5.22	1383 / 5.68	
7000	1007 / 1.70	1042 / 2.02	1079 / 2.36	1117 / 2.72	1156 / 3.11	1195 / 3.51	1234 / 3.93	1273 / 4.37	1312 / 4.81	1351 / 5.28	1388 / 5.75		
7500	1079 / 2.09	1111 / 2.43	1145 / 2.79	1181 / 3.17	1217 / 3.57	1253 / 3.99	1290 / 4.43	1326 / 4.89	1363 / 5.35	1399 / 5.83			
8000	1150 / 2.54	1181 / 2.90	1213 / 3.28	1246 / 3.68	1279 / 4.10	1313 / 4.54	1347 / 4.99	1382 / 5.46					
8500	1222 / 3.05	1251 / 3.43	1281 / 3.82	1312 / 4.24	1343 / 4.68	1375 / 5.14							
9000	1294 / 3.62	1321 / 4.02	1349 / 4.44	1378 / 4.87									
9500	1366 / 4.26	1392 / 4.67											

Max Sizeable RPM = 1400 RPM. Table shown extended beyond this point for reference only.

Motor 186734/A01-ECM-50-480-28 has an rpm range of 300 to 1300.

Motor 186734/A01-ECM-60-480-28 has an rpm range of 300 to 1300.

Motor 186737/A01-ECM-50-240-28 has an rpm range of 300 to 1300.

Motor 186737/A01-ECM-60-240-28 has an rpm range of 300 to 1300.

Motor 186739/A01-ECM-50-480-28 has an rpm range of 300 to 1400.

Motor 186739/A01-ECM-60-480-28 has an rpm range of 300 to 1400.