

RTU1-18-FA

CFM	Static Pressure in Inches W.G.									
	0.000	0.500	1.000	1.500	2.000	2.500	3.000	3.500	4.000	4.500
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
500		740 / 0.11	1022 / 0.28	1238 / 0.49	1420 / 0.72	1577 / 0.98	1724 / 1.27	1859 / 1.57	1976 / 1.88	2092 / 2.22
750		763 / 0.14	1050 / 0.33	1269 / 0.56	1451 / 0.82	1613 / 1.10	1756 / 1.40	1889 / 1.73	2016 / 2.08	2131 / 2.44
1000		787 / 0.16	1074 / 0.38	1294 / 0.63	1479 / 0.92	1642 / 1.22	1789 / 1.56	1923 / 1.91	2045 / 2.27	2165 / 2.66
1250		814 / 0.19	1096 / 0.43	1317 / 0.70	1502 / 1.01	1667 / 1.34	1814 / 1.70	1947 / 2.06	2073 / 2.46	2193 / 2.88
1500		846 / 0.22	1121 / 0.48	1340 / 0.78	1526 / 1.11	1691 / 1.46	1838 / 1.84	1974 / 2.24	2101 / 2.66	
1750		883 / 0.25	1148 / 0.53	1364 / 0.85	1549 / 1.20	1712 / 1.58	1862 / 1.98	1998 / 2.41	2124 / 2.84	
2000	611 / 0.05	926 / 0.29	1179 / 0.59	1391 / 0.93	1574 / 1.30	1736 / 1.70	1885 / 2.13	2020 / 2.57		
2250	687 / 0.07	974 / 0.33	1214 / 0.65	1420 / 1.01	1599 / 1.41	1761 / 1.83	1908 / 2.28	2044 / 2.74		
2500	763 / 0.10	1026 / 0.37	1253 / 0.71	1451 / 1.09	1628 / 1.51	1786 / 1.95	1932 / 2.42	2068 / 2.92		
2750	839 / 0.13	1081 / 0.43	1296 / 0.78	1486 / 1.19	1658 / 1.62	1814 / 2.09	1957 / 2.58			
3000	916 / 0.17	1139 / 0.49	1342 / 0.86	1525 / 1.28	1691 / 1.74	1844 / 2.22	1985 / 2.73			

Max Sizeable RPM = 2600 RPM. Table shown extended beyond this point for reference only.

Motor 00158ET3H145T-W22 has an rpm range of 600 to 1750.

Motor 00158OT3H145T-S has an rpm range of 600 to 1750.

Motor 00218ET3H145T-W22 has an rpm range of 600 to 1750.

Motor 00218OT3H145T-S has an rpm range of 600 to 1750.

Motor BMN145-2.0I2-CS-UB1-50 (1200RPM) has an rpm range of 600 to 1200.

Motor BMN145-2.0I2-CS-UB1-60 (1200RPM) has an rpm range of 600 to 1200.

Motor BMN145-2.0I2-ES-UB1-50 (1800RPM) has an rpm range of 600 to 1800.

Motor BMN145-2.0I2-ES-UB1-60 (1800RPM) has an rpm range of 600 to 1800.

Motor DHP0034 has an rpm range of 600 to 1750.

Motor DTP0024 has an rpm range of 600 to 1740.

Motor DTP0024-50HZ has an rpm range of 600 to 1415.

Motor DTP0032 has an rpm range of 900 to 2600.

Motor DTP1/54 has an rpm range of 600 to 1750.

Motor DTP1/54-50HZ has an rpm range of 600 to 1426.

Motor GP0024 has an rpm range of 600 to 1740.

Motor GP0024-50 has an rpm range of 600 to 1440.

Motor GP1/54 has an rpm range of 600 to 1800.

Motor GP1/54-50 has an rpm range of 600 to 1440.

Motor GT0110 has an rpm range of 600 to 1770.