

RTU1-E.152-16-FA

CFM	Static Pressure in Inches W.G.												
	0.000	0.500	1.000	1.500	2.000	2.500	3.000	3.500	4.000	4.500	5.000	5.500	6.000
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
600			1215 / 0.19	1471 / 0.31	1685 / 0.43	1875 / 0.57	2055 / 0.72	2214 / 0.88	2362 / 1.04	2500 / 1.20	2643 / 1.40	2765 / 1.57	2885 / 1.76
840			1269 / 0.24	1508 / 0.38	1718 / 0.53	1905 / 0.69	2074 / 0.86	2234 / 1.04	2380 / 1.22	2523 / 1.42	2658 / 1.62	2781 / 1.82	2907 / 2.04
1080		1096 / 0.16	1347 / 0.30	1567 / 0.46	1768 / 0.63	1946 / 0.82	2114 / 1.01	2269 / 1.21	2411 / 1.41	2547 / 1.62	2680 / 1.85	2805 / 2.08	2927 / 2.31
1320		1229 / 0.22	1449 / 0.37	1648 / 0.55	1833 / 0.74	2003 / 0.95	2160 / 1.16	2312 / 1.38	2454 / 1.61	2588 / 1.85	2716 / 2.09	2839 / 2.34	2953 / 2.59
1560	1160 / 0.14	1373 / 0.29	1568 / 0.46	1749 / 0.66	1916 / 0.87	2077 / 1.09	2229 / 1.33	2371 / 1.57	2504 / 1.82	2631 / 2.07	2761 / 2.35	2878 / 2.61	2994 / 2.89
1800	1338 / 0.21	1527 / 0.38	1700 / 0.58	1863 / 0.79	2016 / 1.01	2166 / 1.26	2308 / 1.51	2442 / 1.77	2571 / 2.04	2695 / 2.32	2817 / 2.61	2932 / 2.90	
2040	1517 / 0.31	1685 / 0.50	1841 / 0.71	1988 / 0.94	2132 / 1.18	2269 / 1.44	2400 / 1.71	2528 / 1.99	2649 / 2.28	2768 / 2.58	2885 / 2.89	2996 / 3.20	
2280	1695 / 0.43	1846 / 0.64	1990 / 0.87	2125 / 1.12	2255 / 1.38	2382 / 1.65	2505 / 1.94	2624 / 2.23	2740 / 2.54	2854 / 2.86	2961 / 3.18		
2520	1874 / 0.58	2011 / 0.81	2143 / 1.06	2268 / 1.32	2389 / 1.60	2507 / 1.89	2622 / 2.20	2733 / 2.51	2841 / 2.83	2947 / 3.17			
2760	2052 / 0.76	2178 / 1.01	2300 / 1.28	2415 / 1.56	2527 / 1.86	2639 / 2.17	2746 / 2.49	2851 / 2.82	2952 / 3.16				
3000	2230 / 0.98	2347 / 1.25	2459 / 1.53	2568 / 1.84	2674 / 2.15	2775 / 2.47	2876 / 2.81	2976 / 3.16					

Max Sizeable RPM = 3000 RPM. Table shown extended beyond this point for reference only.

Motor 186725/A01-ECM-50-277-16 has an rpm range of 1000 to 2390.

Motor 186725/A01-ECM-60-277-16 has an rpm range of 1000 to 2390.

Motor 186727/A01-ECM-50-480-16 has an rpm range of 1000 to 3000.

Motor 186727/A01-ECM-60-480-16 has an rpm range of 1000 to 3000.

Motor 186728/A01-ECM-50-240-16 has an rpm range of 1000 to 2770.

Motor 186728/A01-ECM-60-240-16 has an rpm range of 1000 to 2770.

Motor 186730/A01-ECM-60-240-18 has an rpm range of 1000 to 2700.