

RTU1-E.152-18-FA

CFM	Static Pressure in Inches W.G.												
	0.000	0.500	1.000	1.500	2.000	2.500	3.000	3.500	4.000	4.500	5.000	5.500	6.000
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
600			1109 / 0.24	1342 / 0.39	1542 / 0.56	1719 / 0.74	1881 / 0.95	2027 / 1.16	2166 / 1.38	2290 / 1.61	2410 / 1.85	2532 / 2.11	2643 / 2.38
840			1138 / 0.29	1370 / 0.47	1567 / 0.67	1739 / 0.87	1900 / 1.10	2044 / 1.33	2182 / 1.58	2308 / 1.83	2428 / 2.09	2545 / 2.37	2658 / 2.66
1080		910 / 0.17	1178 / 0.35	1401 / 0.56	1595 / 0.78	1768 / 1.01	1925 / 1.26	2069 / 1.51	2204 / 1.78	2333 / 2.07	2449 / 2.34	2565 / 2.65	2673 / 2.95
1320		991 / 0.22	1229 / 0.42	1441 / 0.65	1630 / 0.89	1798 / 1.15	1953 / 1.42	2095 / 1.70	2230 / 2.00	2357 / 2.31	2477 / 2.62	2588 / 2.93	2699 / 3.27
1560		1086 / 0.28	1297 / 0.50	1493 / 0.75	1672 / 1.02	1835 / 1.30	1987 / 1.60	2128 / 1.91	2261 / 2.23	2382 / 2.54	2504 / 2.89	2617 / 3.24	
1800	993 / 0.17	1190 / 0.36	1377 / 0.60	1554 / 0.86	1722 / 1.15	1879 / 1.46	2027 / 1.78	2163 / 2.11	2293 / 2.46	2416 / 2.81	2535 / 3.18	2647 / 3.55	
2040	1125 / 0.24	1300 / 0.46	1468 / 0.71	1629 / 0.99	1785 / 1.30	1934 / 1.63	2073 / 1.97	2205 / 2.33	2334 / 2.70	2455 / 3.09	2569 / 3.47	2681 / 3.87	
2280	1258 / 0.34	1414 / 0.57	1566 / 0.84	1714 / 1.15	1857 / 1.47	1995 / 1.82	2129 / 2.18	2255 / 2.56	2377 / 2.95	2495 / 3.36	2609 / 3.78		
2520	1390 / 0.46	1533 / 0.72	1671 / 1.00	1805 / 1.32	1938 / 1.66	2067 / 2.03	2191 / 2.41	2314 / 2.82	2430 / 3.23	2543 / 3.65	2653 / 4.09		
2760	1522 / 0.61	1653 / 0.88	1779 / 1.19	1901 / 1.51	2026 / 1.88	2146 / 2.26	2264 / 2.67	2379 / 3.09	2491 / 3.52	2599 / 3.97			
3000	1655 / 0.78	1775 / 1.07	1893 / 1.40	2008 / 1.75	2122 / 2.13	2234 / 2.53	2344 / 2.95	2451 / 3.38	2558 / 3.84	2662 / 4.31			

Max Sizeable RPM = 2700 RPM. Table shown extended beyond this point for reference only.

Motor 186726/A01-ECM-50-277-18 has an rpm range of 900 to 1950.

Motor 186726/A01-ECM-60-277-18 has an rpm range of 900 to 1950.

Motor 186730/A01-ECM-50-240-18 has an rpm range of 900 to 2700.

Motor 186730/A01-ECM-60-240-18 has an rpm range of 900 to 2700.

Motor 186731/A01-ECM-50-480-18 has an rpm range of 900 to 2700.

Motor 186731/A01-ECM-60-480-18 has an rpm range of 900 to 2700.