

RTU1-E.302-11-FA

CFM	Static Pressure in Inches W.G.									
	0.000	0.250	0.500	0.750	1.000	1.250	1.500	1.750	2.000	2.250
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
900	1187 / 0.13	1391 / 0.23	1552 / 0.33	1685 / 0.43	1807 / 0.54	1923 / 0.65	2032 / 0.76	2138 / 0.88	2239 / 1.00	2338 / 1.13
990	1306 / 0.18	1495 / 0.28	1650 / 0.39	1781 / 0.51	1897 / 0.62	2004 / 0.73	2111 / 0.85	2210 / 0.98	2308 / 1.11	2397 / 1.23
1080	1425 / 0.23	1600 / 0.34	1750 / 0.46	1875 / 0.59	1989 / 0.71	2093 / 0.83	2195 / 0.96	2288 / 1.09	2379 / 1.22	
1170	1544 / 0.29	1708 / 0.41	1851 / 0.54	1973 / 0.68	2082 / 0.81	2187 / 0.95	2281 / 1.08	2373 / 1.22		
1260	1662 / 0.36	1816 / 0.48	1953 / 0.63	2072 / 0.78	2180 / 0.92	2278 / 1.07	2373 / 1.21			
1350	1781 / 0.45	1923 / 0.57	2055 / 0.73	2174 / 0.89	2277 / 1.04	2373 / 1.19				
1440	1900 / 0.54	2034 / 0.67	2162 / 0.84	2275 / 1.01	2376 / 1.17					
1530	2018 / 0.65	2146 / 0.79	2267 / 0.96	2376 / 1.13						
1620	2137 / 0.77	2253 / 0.91	2372 / 1.09							
1710	2256 / 0.91	2372 / 1.06								
1800	2375 / 1.06									

Max Sizeable RPM = 2400 RPM. Table shown extended beyond this point for reference only.

- Motor 00118ET3H143T-W22 has an rpm range of 1000 to 1750.
- Motor 00118OT3H143T-S has an rpm range of 1000 to 1750.
- Motor 00158ET3H145T-W22 has an rpm range of 1000 to 1750.
- Motor 00158OT3H145T-S has an rpm range of 1000 to 1750.
- Motor 00218ET3H145T-W22 has an rpm range of 1000 to 1750.
- Motor 00218OT3H145T-S has an rpm range of 1000 to 1750.
- Motor 00318OT3E56Z-48PP has an rpm range of 1000 to 1730.
- Motor BMN145-2.0I2-CS-UB1-50 (1200RPM) has an rpm range of 1000 to 1200.
- Motor BMN145-2.0I2-CS-UB1-60 (1200RPM) has an rpm range of 1000 to 1200.
- Motor BMN145-2.0I2-ES-UB1-50 (1800RPM) has an rpm range of 1000 to 1800.
- Motor BMN145-2.0I2-ES-UB1-60 (1800RPM) has an rpm range of 1000 to 1800.
- Motor DTP0014 has an rpm range of 1000 to 1750.
- Motor DTP0014-50HZ has an rpm range of 1000 to 1429.
- Motor DTP0016 has an rpm range of 1000 to 1150.
- Motor DTP0022 has an rpm range of 1000 to 2400.
- Motor DTP0024 has an rpm range of 1000 to 1740.
- Motor DTP0024-50HZ has an rpm range of 1000 to 1415.
- Motor DTP0032 has an rpm range of 1000 to 2400.
- Motor DTP1/54-50HZ has an rpm range of 1000 to 1426.
- Motor GP0014 has an rpm range of 1000 to 1800.
- Motor GP0014-50 has an rpm range of 1000 to 1440.
- Motor GP0024 has an rpm range of 1000 to 1740.
- Motor GP0024-50 has an rpm range of 1000 to 1440.
- Motor GP1/54 has an rpm range of 1000 to 1800.
- Motor GP1/54-50 has an rpm range of 1000 to 1440.