

# RTU1-E.304-16-FA

CFM	Static Pressure in Inches W.G.												
	0.000	0.500	1.000	1.500	2.000	2.500	3.000	3.500	4.000	4.500	5.000	5.500	6.000
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
900		1008 / 0.13	1286 / 0.26	1520 / 0.40	1727 / 0.56	1915 / 0.72	2083 / 0.90	2244 / 1.08	2387 / 1.27	2528 / 1.47	2663 / 1.68	2786 / 1.88	2903 / 2.09
1110		1112 / 0.17	1359 / 0.31	1577 / 0.47	1773 / 0.65	1954 / 0.83	2118 / 1.03	2270 / 1.23	2418 / 1.44	2552 / 1.65	2681 / 1.87	2810 / 2.11	2929 / 2.35
1320		1229 / 0.22	1449 / 0.37	1648 / 0.55	1833 / 0.74	2003 / 0.95	2160 / 1.16	2312 / 1.38	2454 / 1.61	2588 / 1.85	2716 / 2.09	2839 / 2.34	2953 / 2.59
1530	1138 / 0.13	1355 / 0.28	1552 / 0.45	1735 / 0.65	1905 / 0.85	2068 / 1.08	2217 / 1.30	2361 / 1.54	2500 / 1.80	2629 / 2.05	2752 / 2.31	2871 / 2.57	2988 / 2.85
1740	1294 / 0.19	1487 / 0.36	1665 / 0.54	1834 / 0.75	1991 / 0.98	2140 / 1.21	2286 / 1.46	2423 / 1.72	2555 / 1.99	2681 / 2.26	2802 / 2.54	2919 / 2.83	
1950	1450 / 0.27	1625 / 0.45	1787 / 0.66	1940 / 0.88	2088 / 1.12	2229 / 1.37	2364 / 1.63	2494 / 1.90	2621 / 2.19	2739 / 2.48	2855 / 2.77	2968 / 3.08	
2160	1606 / 0.36	1765 / 0.56	1915 / 0.79	2055 / 1.02	2193 / 1.28	2325 / 1.54	2452 / 1.82	2574 / 2.11	2693 / 2.41	2809 / 2.72	2923 / 3.04		
2370	1761 / 0.48	1908 / 0.70	2047 / 0.94	2178 / 1.19	2305 / 1.46	2428 / 1.74	2548 / 2.03	2663 / 2.33	2778 / 2.65	2887 / 2.97	2996 / 3.31		
2580	1918 / 0.62	2053 / 0.86	2181 / 1.11	2304 / 1.38	2423 / 1.66	2539 / 1.96	2652 / 2.27	2762 / 2.59	2870 / 2.92	2972 / 3.25			
2790	2074 / 0.78	2200 / 1.04	2319 / 1.31	2435 / 1.59	2546 / 1.89	2655 / 2.20	2762 / 2.53	2864 / 2.86	2968 / 3.20				
3000	2230 / 0.98	2347 / 1.25	2459 / 1.53	2568 / 1.84	2674 / 2.15	2775 / 2.47	2876 / 2.81	2976 / 3.16					

Max Sizeable RPM = 3000 RPM. Table shown extended beyond this point for reference only.

Motor 186725/A01-ECM-50-277-16 has an rpm range of 1000 to 2390.

Motor 186725/A01-ECM-60-277-16 has an rpm range of 1000 to 2390.

Motor 186727/A01-ECM-50-480-16 has an rpm range of 1000 to 3000.

Motor 186727/A01-ECM-60-480-16 has an rpm range of 1000 to 3000.

Motor 186728/A01-ECM-50-240-16 has an rpm range of 1000 to 2770.

Motor 186728/A01-ECM-60-240-16 has an rpm range of 1000 to 2770.

Motor 186730/A01-ECM-60-240-18 has an rpm range of 1000 to 2700.