

RTU1-E.402-13-FA

CFM	Static Pressure in Inches W.G.										
	0.000	0.250	0.500	0.750	1.000	1.250	1.500	1.750	2.000	2.250	2.500
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
1100				1341 / 0.48	1477 / 0.62	1603 / 0.77	1724 / 0.93	1839 / 1.10	1947 / 1.27	2052 / 1.46	2148 / 1.65
1290			1311 / 0.44	1437 / 0.59	1558 / 0.75	1675 / 0.91	1787 / 1.09	1894 / 1.27	1997 / 1.45	2098 / 1.65	2194 / 1.85
1480		1312 / 0.40	1433 / 0.56	1543 / 0.72	1654 / 0.90	1760 / 1.08	1862 / 1.27	1963 / 1.46	2058 / 1.66	2154 / 1.87	2246 / 2.08
1670	1318 / 0.38	1448 / 0.54	1559 / 0.71	1662 / 0.89	1762 / 1.08	1858 / 1.27	1951 / 1.47	2044 / 1.68	2133 / 1.90	2224 / 2.12	
1860	1468 / 0.53	1588 / 0.70	1691 / 0.88	1785 / 1.08	1877 / 1.28	1964 / 1.49	2051 / 1.71	2135 / 1.93	2220 / 2.17		
2050	1617 / 0.71	1728 / 0.89	1824 / 1.09	1912 / 1.30	1998 / 1.52	2079 / 1.75	2160 / 1.98	2238 / 2.22			
2240	1767 / 0.92	1871 / 1.12	1960 / 1.34	2044 / 1.56	2123 / 1.80	2200 / 2.04	2274 / 2.29				
2430	1916 / 1.18	2013 / 1.39	2098 / 1.62	2177 / 1.87	2252 / 2.12						
2620	2065 / 1.48	2158 / 1.71	2237 / 1.95								
2810	2216 / 1.82										

Max Sizeable RPM = 2300 RPM. Table shown extended beyond this point for reference only.

Motor 00118ET3H143T-W22 has an rpm range of 1200 to 1750.

Motor 00118OT3H143T-S has an rpm range of 1200 to 1750.

Motor 00158ET3H145T-W22 has an rpm range of 1200 to 1750.

Motor 00158OT3H145T-S has an rpm range of 1200 to 1750.

Motor 00218ET3H145T-W22 has an rpm range of 1200 to 1750.

Motor 00218OT3H145T-S has an rpm range of 1200 to 1750.

Motor BMN145-2.0I2-ES-UB1-50 (1800RPM) has an rpm range of 1200 to 1800.

Motor BMN145-2.0I2-ES-UB1-60 (1800RPM) has an rpm range of 1200 to 1800.

Motor DTP0014 has an rpm range of 1200 to 1750.

Motor DTP0014-50HZ has an rpm range of 1200 to 1429.

Motor DTP0022 has an rpm range of 1200 to 2300.

Motor DTP0024 has an rpm range of 1200 to 1740.

Motor DTP0024-50HZ has an rpm range of 1200 to 1415.

Motor DTP0032 has an rpm range of 1200 to 2300.

Motor DTP1/54 has an rpm range of 1200 to 1750.

Motor DTP1/54-50HZ has an rpm range of 1200 to 1426.

Motor GP0014 has an rpm range of 1200 to 1800.

Motor GP0014-50 has an rpm range of 1200 to 1440.

Motor GP0024 has an rpm range of 1200 to 1740.

Motor GP0024-50 has an rpm range of 1200 to 1440.

Motor GP1/54 has an rpm range of 1200 to 1800.

Motor GP1/54-50 has an rpm range of 1200 to 1440.