

RTU1-I.100-18-FA

CFM	Static Pressure in Inches W.G.												
	0.000	0.500	1.000	1.500	2.000	2.500	3.000	3.500	4.000	4.500	5.000	5.500	6.000
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
600			1119 / 0.24	1354 / 0.40	1550 / 0.57	1729 / 0.77	1887 / 0.98	2034 / 1.20	2174 / 1.44	2299 / 1.67	2419 / 1.91	2542 / 2.18	2643 / 2.42
840			1160 / 0.30	1388 / 0.48	1582 / 0.67	1757 / 0.89	1913 / 1.12	2059 / 1.36	2193 / 1.62	2320 / 1.89	2442 / 2.17	2561 / 2.47	2667 / 2.75
1080		953 / 0.20	1213 / 0.39	1430 / 0.58	1622 / 0.80	1791 / 1.03	1946 / 1.27	2089 / 1.54	2222 / 1.81	2348 / 2.10	2471 / 2.41	2584 / 2.72	2693 / 3.04
1320		1045 / 0.26	1279 / 0.48	1485 / 0.71	1667 / 0.94	1774 / 1.10	1985 / 1.46	2126 / 1.74	2256 / 2.03	2383 / 2.34	2500 / 2.65	2614 / 2.98	
1560	933 / 0.16	1151 / 0.33	1359 / 0.58	1551 / 0.85	1724 / 1.12	1882 / 1.39	2031 / 1.68	2167 / 1.97	2297 / 2.29	2419 / 2.60	2537 / 2.94	2649 / 3.29	
1800	1077 / 0.24	1265 / 0.42	1452 / 0.69	1626 / 0.99	1789 / 1.30	1942 / 1.61	2083 / 1.93	2217 / 2.25	2344 / 2.58	2466 / 2.93	2579 / 3.28	2691 / 3.65	
2040	1219 / 0.35	1387 / 0.53	1553 / 0.82	1713 / 1.15	1865 / 1.50	2008 / 1.84	2145 / 2.20	2274 / 2.55	2397 / 2.91	2515 / 3.29	2625 / 3.65		
2280	1364 / 0.49	1512 / 0.68	1662 / 0.98	1808 / 1.33	1949 / 1.70	2084 / 2.09	2214 / 2.48	2338 / 2.87	2457 / 3.27	2570 / 3.67	2679 / 4.07		
2520	1507 / 0.66	1642 / 0.86	1777 / 1.16	1911 / 1.53	2042 / 1.93	2169 / 2.35	2291 / 2.77	2409 / 3.20	2523 / 3.63	2633 / 4.07			
2760	1651 / 0.87	1773 / 1.07	1897 / 1.38	2020 / 1.77	2141 / 2.19	2260 / 2.63	2375 / 3.09	2489 / 3.56	2596 / 4.02				
3000	1794 / 1.12	1906 / 1.32	2020 / 1.64	2134 / 2.03	2247 / 2.47	2358 / 2.94	2467 / 3.43	2573 / 3.92	2676 / 4.43				

Max Sizeable RPM = 2700 RPM. Table shown extended beyond this point for reference only.

Motor 186726/A01-ECM-50-277-18 has an rpm range of 900 to 1950.

Motor 186726/A01-ECM-60-277-18 has an rpm range of 900 to 1950.

Motor 186730/A01-ECM-50-240-18 has an rpm range of 900 to 2700.

Motor 186730/A01-ECM-60-240-18 has an rpm range of 900 to 2700.

Motor 186731/A01-ECM-50-480-18 has an rpm range of 900 to 2700.

Motor 186731/A01-ECM-60-480-18 has an rpm range of 900 to 2700.