

RTU1-I.100HE-11-FA

CFM	Static Pressure in Inches W.G.									
	0.000	0.250	0.500	0.750	1.000	1.250	1.500	1.750	2.000	2.250
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
550		1026 / 0.10	1217 / 0.16	1385 / 0.24	1549 / 0.32	1703 / 0.42	1852 / 0.54	1993 / 0.66	2124 / 0.79	2254 / 0.94
660	915 / 0.06	1150 / 0.14	1325 / 0.21	1477 / 0.29	1622 / 0.38	1755 / 0.48	1886 / 0.58	2018 / 0.70	2143 / 0.83	2260 / 0.97
770	1066 / 0.10	1279 / 0.18	1442 / 0.27	1584 / 0.36	1711 / 0.45	1838 / 0.56	1954 / 0.66	2070 / 0.78	2181 / 0.90	2299 / 1.05
880	1219 / 0.15	1413 / 0.24	1563 / 0.34	1699 / 0.45	1818 / 0.55	1934 / 0.66	2042 / 0.77	2146 / 0.88	2251 / 1.01	2353 / 1.14
990	1371 / 0.21	1547 / 0.31	1692 / 0.43	1820 / 0.54	1934 / 0.66	2041 / 0.77	2143 / 0.89	2240 / 1.02	2335 / 1.14	
1100	1524 / 0.28	1687 / 0.40	1824 / 0.53	1943 / 0.66	2052 / 0.78	2153 / 0.91	2249 / 1.04	2340 / 1.17		
1210	1676 / 0.38	1825 / 0.51	1955 / 0.65	2072 / 0.79	2176 / 0.93	2274 / 1.07	2363 / 1.20			
1320	1828 / 0.49	1967 / 0.63	2089 / 0.78	2200 / 0.93	2300 / 1.08	2396 / 1.24	2316 / 1.11			
1430	1981 / 0.62	2109 / 0.77	2227 / 0.94	2333 / 1.10						
1540	2133 / 0.78	2255 / 0.94	2362 / 1.11							
1650	2285 / 0.96	2398 / 1.13								

Max Sizeable RPM = 2400 RPM. Table shown extended beyond this point for reference only.

- Motor 00118ET3H143T-W22 has an rpm range of 900 to 1750.
- Motor 00118OT3H143T-S has an rpm range of 900 to 1750.
- Motor 00158ET3H145T-W22 has an rpm range of 900 to 1750.
- Motor 00158OT3H145T-S has an rpm range of 900 to 1750.
- Motor 00218ET3H145T-W22 has an rpm range of 900 to 1750.
- Motor 00218OT3H145T-S has an rpm range of 900 to 1750.
- Motor 00318OT3E56Z-48PP has an rpm range of 900 to 1730.
- Motor BMN145-2.0I2-CS-UB1-50 (1200RPM) has an rpm range of 900 to 1200.
- Motor BMN145-2.0I2-CS-UB1-60 (1200RPM) has an rpm range of 900 to 1200.
- Motor BMN145-2.0I2-ES-UB1-50 (1800RPM) has an rpm range of 900 to 1800.
- Motor BMN145-2.0I2-ES-UB1-60 (1800RPM) has an rpm range of 900 to 1800.
- Motor DTP0014 has an rpm range of 900 to 1750.
- Motor DTP0014-50HZ has an rpm range of 900 to 1429.
- Motor DTP0016 has an rpm range of 900 to 1150.
- Motor DTP0022 has an rpm range of 900 to 2400.
- Motor DTP0024 has an rpm range of 900 to 1740.
- Motor DTP0024-50HZ has an rpm range of 900 to 1415.
- Motor DTP0032 has an rpm range of 900 to 2400.
- Motor DTP1/54-50HZ has an rpm range of 900 to 1426.
- Motor GP0014 has an rpm range of 900 to 1800.
- Motor GP0014-50 has an rpm range of 900 to 1440.
- Motor GP0024 has an rpm range of 900 to 1740.
- Motor GP0024-50 has an rpm range of 900 to 1440.
- Motor GP1/54 has an rpm range of 900 to 1800.
- Motor GP1/54-50 has an rpm range of 900 to 1440.