

RTU1-I.125HE-11-FA

CFM	Static Pressure in Inches W.G.									
	0.000	0.250	0.500	0.750	1.000	1.250	1.500	1.750	2.000	2.250
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
600		1073 / 0.11	1258 / 0.18	1418 / 0.26	1571 / 0.34	1714 / 0.44	1858 / 0.55	1993 / 0.67	2120 / 0.80	2247 / 0.94
710	969 / 0.07	1197 / 0.15	1368 / 0.23	1517 / 0.32	1651 / 0.41	1784 / 0.50	1909 / 0.61	2029 / 0.72	2152 / 0.86	2268 / 0.99
820	1117 / 0.11	1325 / 0.20	1486 / 0.30	1624 / 0.39	1752 / 0.49	1868 / 0.59	1985 / 0.70	2097 / 0.82	2204 / 0.94	2310 / 1.07
930	1267 / 0.16	1455 / 0.26	1609 / 0.37	1738 / 0.48	1860 / 0.59	1970 / 0.70	2076 / 0.81	2178 / 0.93	2279 / 1.06	2379 / 1.19
1040	1417 / 0.23	1590 / 0.34	1733 / 0.46	1860 / 0.58	1973 / 0.70	2076 / 0.81	2176 / 0.94	2276 / 1.07	2369 / 1.20	
1150	1567 / 0.31	1727 / 0.43	1864 / 0.56	1983 / 0.69	2091 / 0.82	2190 / 0.95	2286 / 1.09	2376 / 1.22		
1260	1717 / 0.40	1864 / 0.53	1994 / 0.68	2111 / 0.83	2214 / 0.97	2312 / 1.12	2400 / 1.26			
1370	1866 / 0.52	2003 / 0.66	2127 / 0.81	2239 / 0.97	2338 / 1.13					
1480	2016 / 0.65	2142 / 0.80	2260 / 0.97	2364 / 1.14						
1590	2166 / 0.81	2284 / 0.97	2395 / 1.14							
1700	2316 / 0.99									

Max Sizeable RPM = 2400 RPM. Table shown extended beyond this point for reference only.

- Motor 00118ET3H143T-W22 has an rpm range of 900 to 1750.
- Motor 00118OT3H143T-S has an rpm range of 900 to 1750.
- Motor 00158ET3H145T-W22 has an rpm range of 900 to 1750.
- Motor 00158OT3H145T-S has an rpm range of 900 to 1750.
- Motor 00218ET3H145T-W22 has an rpm range of 900 to 1750.
- Motor 00218OT3H145T-S has an rpm range of 900 to 1750.
- Motor 00318OT3E56Z-48PP has an rpm range of 900 to 1730.
- Motor BMN145-2.0I2-CS-UB1-50 (1200RPM) has an rpm range of 900 to 1200.
- Motor BMN145-2.0I2-CS-UB1-60 (1200RPM) has an rpm range of 900 to 1200.
- Motor BMN145-2.0I2-ES-UB1-50 (1800RPM) has an rpm range of 900 to 1800.
- Motor BMN145-2.0I2-ES-UB1-60 (1800RPM) has an rpm range of 900 to 1800.
- Motor DTP0014 has an rpm range of 900 to 1750.
- Motor DTP0014-50HZ has an rpm range of 900 to 1429.
- Motor DTP0016 has an rpm range of 900 to 1150.
- Motor DTP0022 has an rpm range of 900 to 2400.
- Motor DTP0024 has an rpm range of 900 to 1740.
- Motor DTP0024-50HZ has an rpm range of 900 to 1415.
- Motor DTP0032 has an rpm range of 900 to 2400.
- Motor DTP1/54-50HZ has an rpm range of 900 to 1426.
- Motor GP0014 has an rpm range of 900 to 1800.
- Motor GP0014-50 has an rpm range of 900 to 1440.
- Motor GP0024 has an rpm range of 900 to 1740.
- Motor GP0024-50 has an rpm range of 900 to 1440.
- Motor GP1/54 has an rpm range of 900 to 1800.
- Motor GP1/54-50 has an rpm range of 900 to 1440.