

RTU1-I.125HE-16-FA

CFM	Static Pressure in Inches W.G.												
	0.000	0.500	1.000	1.500	2.000	2.500	3.000	3.500	4.000	4.500	5.000	5.500	6.000
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
600			1227 / 0.19	1478 / 0.31	1695 / 0.44	1887 / 0.58	2062 / 0.73	2222 / 0.89	2372 / 1.05	2510 / 1.22	2643 / 1.40	2778 / 1.59	2899 / 1.78
840		1006 / 0.13	1288 / 0.25	1525 / 0.39	1732 / 0.54	1918 / 0.70	2090 / 0.88	2246 / 1.05	2393 / 1.24	2530 / 1.43	2667 / 1.63	2791 / 1.84	2907 / 2.04
1080		1129 / 0.18	1376 / 0.32	1593 / 0.48	1788 / 0.65	1967 / 0.84	2130 / 1.03	2283 / 1.23	2427 / 1.43	2565 / 1.65	2693 / 1.87	2820 / 2.10	2935 / 2.33
1320	1034 / 0.11	1269 / 0.24	1486 / 0.41	1684 / 0.59	1864 / 0.78	2034 / 0.99	2189 / 1.20	2336 / 1.42	2477 / 1.65	2609 / 1.89	2739 / 2.14	2857 / 2.38	2973 / 2.64
1560	1222 / 0.18	1423 / 0.33	1613 / 0.51	1791 / 0.71	1960 / 0.93	2117 / 1.15	2264 / 1.39	2404 / 1.63	2541 / 1.89	2667 / 2.14	2791 / 2.41	2910 / 2.69	
1800	1408 / 0.27	1586 / 0.44	1754 / 0.64	1915 / 0.86	2069 / 1.10	2214 / 1.34	2353 / 1.60	2486 / 1.86	2612 / 2.13	2736 / 2.41	2857 / 2.71	2970 / 3.00	
2040	1596 / 0.39	1754 / 0.59	1905 / 0.80	2050 / 1.04	2191 / 1.29	2326 / 1.56	2455 / 1.83	2582 / 2.12	2702 / 2.41	2818 / 2.71	2931 / 3.02		
2280	1784 / 0.55	1926 / 0.76	2063 / 1.00	2194 / 1.25	2324 / 1.52	2449 / 1.80	2570 / 2.10	2689 / 2.40	2801 / 2.71	2912 / 3.03			
2520	1972 / 0.74	2100 / 0.97	2226 / 1.23	2346 / 1.50	2466 / 1.79	2582 / 2.09	2695 / 2.40	2806 / 2.73	2913 / 3.06				
2760	2160 / 0.97	2277 / 1.23	2392 / 1.50	2505 / 1.79	2614 / 2.10	2722 / 2.41	2828 / 2.75	2930 / 3.08					
3000	2347 / 1.24	2457 / 1.52	2562 / 1.82	2667 / 2.13	2770 / 2.45	2868 / 2.78	2967 / 3.13						

Max Sizeable RPM = 3000 RPM. Table shown extended beyond this point for reference only.

Motor 186725/A01-ECM-50-277-16 has an rpm range of 1000 to 2390.

Motor 186725/A01-ECM-60-277-16 has an rpm range of 1000 to 2390.

Motor 186727/A01-ECM-50-480-16 has an rpm range of 1000 to 3000.

Motor 186727/A01-ECM-60-480-16 has an rpm range of 1000 to 3000.

Motor 186728/A01-ECM-50-240-16 has an rpm range of 1000 to 2770.

Motor 186728/A01-ECM-60-240-16 has an rpm range of 1000 to 2770.

Motor 186730/A01-ECM-60-240-18 has an rpm range of 1000 to 2700.