

RTU1-I.125HE-18-FA

CFM	Static Pressure in Inches W.G.												
	0.000	0.500	1.000	1.500	2.000	2.500	3.000	3.500	4.000	4.500	5.000	5.500	6.000
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
600			1117 / 0.24	1351 / 0.39	1550 / 0.57	1724 / 0.75	1887 / 0.96	2034 / 1.17	2166 / 1.38	2299 / 1.63	2419 / 1.87	2532 / 2.11	2643 / 2.38
840			1155 / 0.30	1384 / 0.48	1579 / 0.68	1754 / 0.89	1909 / 1.11	2054 / 1.34	2193 / 1.60	2320 / 1.86	2442 / 2.12	2553 / 2.39	2667 / 2.69
1080		946 / 0.19	1207 / 0.38	1425 / 0.58	1617 / 0.80	1785 / 1.03	1942 / 1.29	2085 / 1.54	2218 / 1.81	2343 / 2.09	2466 / 2.39	2578 / 2.68	2693 / 3.01
1320		1036 / 0.25	1270 / 0.46	1477 / 0.69	1660 / 0.94	1826 / 1.20	1979 / 1.47	2119 / 1.75	2253 / 2.05	2378 / 2.36	2495 / 2.67	2609 / 2.99	
1560	921 / 0.15	1140 / 0.33	1348 / 0.56	1540 / 0.82	1714 / 1.09	1875 / 1.38	2023 / 1.67	2161 / 1.98	2291 / 2.30	2415 / 2.64	2528 / 2.96	2644 / 3.33	
1800	1063 / 0.23	1252 / 0.43	1438 / 0.68	1614 / 0.96	1779 / 1.26	1931 / 1.57	2074 / 1.89	2209 / 2.23	2335 / 2.57	2456 / 2.93	2571 / 3.30	2683 / 3.67	
2040	1204 / 0.33	1371 / 0.56	1537 / 0.83	1699 / 1.13	1851 / 1.45	1996 / 1.78	2132 / 2.13	2262 / 2.49	2386 / 2.86	2503 / 3.24	2615 / 3.63		
2280	1346 / 0.47	1495 / 0.71	1645 / 1.00	1791 / 1.32	1934 / 1.66	2069 / 2.02	2199 / 2.39	2324 / 2.78	2444 / 3.18	2556 / 3.58	2667 / 4.00		
2520	1488 / 0.63	1622 / 0.90	1759 / 1.21	1892 / 1.54	2024 / 1.90	2152 / 2.29	2274 / 2.68	2393 / 3.09	2507 / 3.52	2617 / 3.94			
2760	1628 / 0.83	1752 / 1.12	1876 / 1.44	2000 / 1.80	2121 / 2.18	2240 / 2.58	2357 / 3.01	2469 / 3.44	2577 / 3.88	2685 / 4.34			
3000	1771 / 1.06	1883 / 1.37	1997 / 1.72	2111 / 2.09	2226 / 2.50	2336 / 2.92	2445 / 3.36	2551 / 3.81	2655 / 4.28				

Max Sizeable RPM = 2700 RPM. Table shown extended beyond this point for reference only.

Motor 186726/A01-ECM-50-277-18 has an rpm range of 900 to 1950.

Motor 186726/A01-ECM-60-277-18 has an rpm range of 900 to 1950.

Motor 186730/A01-ECM-50-240-18 has an rpm range of 900 to 2700.

Motor 186730/A01-ECM-60-240-18 has an rpm range of 900 to 2700.

Motor 186731/A01-ECM-50-480-18 has an rpm range of 900 to 2700.

Motor 186731/A01-ECM-60-480-18 has an rpm range of 900 to 2700.