

RTU1-I.150-16-FA

CFM	Static Pressure in Inches W.G.												
	0.000	0.500	1.000	1.500	2.000	2.500	3.000	3.500	4.000	4.500	5.000	5.500	6.000
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
750			1250 / 0.22	1497 / 0.36	1708 / 0.50	1894 / 0.65	2066 / 0.81	2226 / 0.98	2373 / 1.15	2517 / 1.34	2650 / 1.53	2778 / 1.73	2896 / 1.93
975		1052 / 0.14	1316 / 0.28	1545 / 0.43	1750 / 0.59	1931 / 0.76	2101 / 0.95	2257 / 1.14	2401 / 1.33	2539 / 1.54	2671 / 1.75	2794 / 1.96	2919 / 2.20
1200		1172 / 0.19	1405 / 0.34	1615 / 0.51	1805 / 0.69	1980 / 0.89	2143 / 1.09	2294 / 1.30	2439 / 1.52	2575 / 1.75	2703 / 1.98	2824 / 2.21	2941 / 2.46
1425	1078 / 0.11	1306 / 0.26	1511 / 0.42	1700 / 0.61	1877 / 0.81	2044 / 1.02	2199 / 1.25	2344 / 1.48	2483 / 1.71	2615 / 1.96	2740 / 2.21	2861 / 2.47	2981 / 2.75
1650	1247 / 0.18	1447 / 0.34	1630 / 0.52	1803 / 0.72	1967 / 0.94	2121 / 1.17	2266 / 1.41	2409 / 1.67	2542 / 1.93	2670 / 2.20	2792 / 2.47	2910 / 2.75	
1875	1417 / 0.26	1596 / 0.44	1761 / 0.64	1917 / 0.86	2063 / 1.08	2211 / 1.34	2350 / 1.60	2480 / 1.86	2608 / 2.14	2729 / 2.43	2850 / 2.73	2962 / 3.02	
2100	1587 / 0.36	1749 / 0.56	1899 / 0.78	2043 / 1.01	2181 / 1.26	2313 / 1.53	2442 / 1.80	2567 / 2.09	2689 / 2.39	2804 / 2.69	2917 / 3.00		
2325	1757 / 0.49	1904 / 0.71	2043 / 0.95	2175 / 1.20	2302 / 1.46	2427 / 1.74	2547 / 2.03	2663 / 2.34	2778 / 2.65	2888 / 2.97	2996 / 3.30		
2550	1927 / 0.65	2063 / 0.89	2189 / 1.14	2312 / 1.41	2431 / 1.69	2547 / 1.99	2659 / 2.29	2769 / 2.61	2878 / 2.95	2982 / 3.28			
2775	2098 / 0.84	2222 / 1.09	2340 / 1.37	2454 / 1.65	2565 / 1.95	2673 / 2.26	2781 / 2.59	2882 / 2.92	2984 / 3.26				
3000	2268 / 1.06	2383 / 1.33	2494 / 1.62	2600 / 1.93	2705 / 2.25	2806 / 2.57	2907 / 2.92						

Max Sizeable RPM = 3000 RPM. Table shown extended beyond this point for reference only.

Motor 186725/A01-ECM-50-277-16 has an rpm range of 1000 to 2390.

Motor 186725/A01-ECM-60-277-16 has an rpm range of 1000 to 2390.

Motor 186727/A01-ECM-50-480-16 has an rpm range of 1000 to 3000.

Motor 186727/A01-ECM-60-480-16 has an rpm range of 1000 to 3000.

Motor 186728/A01-ECM-50-240-16 has an rpm range of 1000 to 2770.

Motor 186728/A01-ECM-60-240-16 has an rpm range of 1000 to 2770.

Motor 186730/A01-ECM-60-240-18 has an rpm range of 1000 to 2700.