

RTU1-I.150HE-16-FA

CFM	Static Pressure in Inches W.G.												
	0.000	0.500	1.000	1.500	2.000	2.500	3.000	3.500	4.000	4.500	5.000	5.500	6.000
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
750			1256 / 0.23	1500 / 0.36	1712 / 0.50	1899 / 0.65	2072 / 0.81	2232 / 0.98	2381 / 1.16	2517 / 1.34	2650 / 1.53	2778 / 1.73	2896 / 1.93
975		1061 / 0.15	1325 / 0.28	1553 / 0.43	1754 / 0.60	1938 / 0.77	2106 / 0.95	2262 / 1.15	2407 / 1.34	2546 / 1.55	2679 / 1.76	2802 / 1.98	2919 / 2.20
1200		1183 / 0.20	1415 / 0.35	1624 / 0.52	1815 / 0.71	1990 / 0.90	2151 / 1.10	2303 / 1.32	2444 / 1.53	2581 / 1.76	2709 / 1.99	2830 / 2.23	2948 / 2.47
1425	1095 / 0.12	1319 / 0.27	1524 / 0.43	1715 / 0.62	1890 / 0.82	2056 / 1.04	2209 / 1.26	2355 / 1.50	2491 / 1.73	2624 / 1.98	2751 / 2.24	2867 / 2.49	2987 / 2.76
1650	1268 / 0.19	1465 / 0.35	1647 / 0.54	1817 / 0.74	1981 / 0.96	2135 / 1.19	2282 / 1.44	2419 / 1.69	2554 / 1.95	2679 / 2.21	2801 / 2.49	2920 / 2.78	
1875	1441 / 0.28	1616 / 0.46	1781 / 0.66	1935 / 0.88	2086 / 1.12	2229 / 1.37	2364 / 1.63	2497 / 1.90	2622 / 2.18	2745 / 2.47	2863 / 2.76	2976 / 3.06	
2100	1614 / 0.39	1771 / 0.59	1920 / 0.81	2063 / 1.05	2199 / 1.30	2333 / 1.57	2462 / 1.85	2586 / 2.13	2706 / 2.43	2823 / 2.74	2933 / 3.05		
2325	1787 / 0.53	1929 / 0.75	2067 / 0.99	2198 / 1.24	2325 / 1.51	2447 / 1.79	2569 / 2.09	2685 / 2.39	2798 / 2.71	2910 / 3.04			
2550	1960 / 0.70	2090 / 0.94	2215 / 1.20	2337 / 1.47	2457 / 1.76	2571 / 2.05	2684 / 2.37	2793 / 2.68	2901 / 3.02				
2775	2133 / 0.90	2254 / 1.16	2370 / 1.44	2482 / 1.73	2593 / 2.03	2702 / 2.35	2806 / 2.67	2909 / 3.01					
3000	2306 / 1.14	2417 / 1.42	2525 / 1.71	2632 / 2.02	2735 / 2.34	2836 / 2.67	2935 / 3.02						

Max Sizeable RPM = 3000 RPM. Table shown extended beyond this point for reference only.

Motor 186725/A01-ECM-50-277-16 has an rpm range of 1000 to 2390.

Motor 186725/A01-ECM-60-277-16 has an rpm range of 1000 to 2390.

Motor 186727/A01-ECM-50-480-16 has an rpm range of 1000 to 3000.

Motor 186727/A01-ECM-60-480-16 has an rpm range of 1000 to 3000.

Motor 186728/A01-ECM-50-240-16 has an rpm range of 1000 to 2770.

Motor 186728/A01-ECM-60-240-16 has an rpm range of 1000 to 2770.

Motor 186730/A01-ECM-60-240-18 has an rpm range of 1000 to 2700.