

RTU1-I.150HE-18-FA

CFM	Static Pressure in Inches W.G.												
	0.000	0.500	1.000	1.500	2.000	2.500	3.000	3.500	4.000	4.500	5.000	5.500	6.000
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
750			1135 / 0.28	1366 / 0.44	1562 / 0.63	1740 / 0.83	1899 / 1.05	2044 / 1.27	2180 / 1.51	2308 / 1.76	2427 / 2.01	2542 / 2.28	2660 / 2.58
975		900 / 0.17	1175 / 0.34	1399 / 0.53	1593 / 0.74	1766 / 0.96	1923 / 1.20	2066 / 1.44	2201 / 1.70	2327 / 1.97	2450 / 2.26	2566 / 2.55	2671 / 2.84
1200		974 / 0.21	1224 / 0.41	1439 / 0.62	1628 / 0.86	1796 / 1.10	1951 / 1.36	2094 / 1.63	2230 / 1.92	2353 / 2.20	2474 / 2.51	2586 / 2.82	2697 / 3.14
1425		1062 / 0.27	1286 / 0.48	1489 / 0.73	1671 / 0.98	1834 / 1.25	1985 / 1.53	2127 / 1.83	2258 / 2.13	2383 / 2.45	2504 / 2.78	2615 / 3.11	
1650	952 / 0.16	1160 / 0.35	1360 / 0.58	1548 / 0.84	1721 / 1.12	1879 / 1.41	2027 / 1.72	2165 / 2.04	2295 / 2.37	2416 / 2.70	2535 / 3.06	2644 / 3.41	
1875	1081 / 0.23	1264 / 0.44	1445 / 0.69	1616 / 0.97	1779 / 1.27	1931 / 1.59	2072 / 1.92	2206 / 2.26	2335 / 2.62	2454 / 2.98	2568 / 3.35	2679 / 3.73	
2100	1211 / 0.33	1374 / 0.55	1537 / 0.82	1695 / 1.12	1845 / 1.44	1989 / 1.78	2126 / 2.13	2256 / 2.50	2378 / 2.87	2497 / 3.26	2609 / 3.65		
2325	1341 / 0.45	1488 / 0.69	1636 / 0.98	1780 / 1.29	1921 / 1.63	2056 / 1.99	2187 / 2.37	2311 / 2.75	2429 / 3.15	2544 / 3.56	2654 / 3.98		
2550	1471 / 0.59	1605 / 0.85	1739 / 1.15	1874 / 1.49	2003 / 1.84	2130 / 2.22	2255 / 2.62	2372 / 3.02	2488 / 3.45	2597 / 3.88			
2775	1600 / 0.76	1724 / 1.04	1848 / 1.36	1971 / 1.71	2093 / 2.09	2211 / 2.48	2328 / 2.90	2441 / 3.33	2537 / 3.71	2658 / 4.23			
3000	1730 / 0.96	1844 / 1.26	1960 / 1.60	2073 / 1.97	2187 / 2.36	2299 / 2.78	2408 / 3.21	2515 / 3.65	2620 / 4.12				

Max Sizeable RPM = 2700 RPM. Table shown extended beyond this point for reference only.

Motor 186726/A01-ECM-50-277-18 has an rpm range of 900 to 1950.

Motor 186726/A01-ECM-60-277-18 has an rpm range of 900 to 1950.

Motor 186730/A01-ECM-50-240-18 has an rpm range of 900 to 2700.

Motor 186730/A01-ECM-60-240-18 has an rpm range of 900 to 2700.

Motor 186731/A01-ECM-50-480-18 has an rpm range of 900 to 2700.

Motor 186731/A01-ECM-60-480-18 has an rpm range of 900 to 2700.