

RTU1-I.200-16-FA

CFM	Static Pressure in Inches W.G.												
	0.000	0.500	1.000	1.500	2.000	2.500	3.000	3.500	4.000	4.500	5.000	5.500	6.000
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
1100		1100 / 0.16	1348 / 0.30	1569 / 0.46	1766 / 0.64	1947 / 0.82	2111 / 1.01	2268 / 1.22	2412 / 1.43	2546 / 1.64	2676 / 1.86	2806 / 2.10	2926 / 2.33
1290		1203 / 0.20	1427 / 0.36	1631 / 0.53	1817 / 0.72	1991 / 0.93	2150 / 1.13	2299 / 1.35	2443 / 1.58	2575 / 1.81	2704 / 2.05	2768 / 2.17	2945 / 2.55
1480	1088 / 0.11	1314 / 0.25	1516 / 0.42	1703 / 0.61	1878 / 0.81	2044 / 1.03	2196 / 1.26	2342 / 1.49	2479 / 1.73	2610 / 1.98	2736 / 2.24	2857 / 2.51	2972 / 2.77
1670	1228 / 0.16	1431 / 0.32	1615 / 0.50	1788 / 0.70	1951 / 0.92	2106 / 1.15	2254 / 1.39	2393 / 1.64	2526 / 1.90	2655 / 2.17	2779 / 2.45	2894 / 2.72	
1860	1368 / 0.22	1553 / 0.39	1721 / 0.59	1881 / 0.80	2033 / 1.03	2178 / 1.28	2319 / 1.54	2451 / 1.80	2580 / 2.08	2703 / 2.36	2822 / 2.65	2938 / 2.95	
2050	1507 / 0.29	1676 / 0.48	1832 / 0.69	1981 / 0.92	2124 / 1.17	2260 / 1.42	2392 / 1.69	2518 / 1.97	2642 / 2.26	2763 / 2.57	2875 / 2.87	2988 / 3.19	
2240	1647 / 0.38	1802 / 0.59	1948 / 0.81	2086 / 1.05	2220 / 1.31	2348 / 1.58	2472 / 1.86	2596 / 2.16	2712 / 2.46	2825 / 2.77	2936 / 3.10		
2430	1787 / 0.49	1932 / 0.71	2066 / 0.95	2197 / 1.21	2321 / 1.47	2442 / 1.76	2561 / 2.05	2676 / 2.36	2787 / 2.68	2896 / 3.00			
2620	1926 / 0.62	2061 / 0.85	2189 / 1.11	2310 / 1.38	2428 / 1.66	2544 / 1.96	2655 / 2.26	2764 / 2.58	2870 / 2.91	2974 / 3.25			
2810	2065 / 0.76	2192 / 1.01	2313 / 1.28	2427 / 1.56	2538 / 1.86	2648 / 2.17	2755 / 2.50	2859 / 2.83	2961 / 3.18				
3000	2206 / 0.92	2324 / 1.19	2437 / 1.48	2547 / 1.77	2653 / 2.09	2755 / 2.41	2857 / 2.75	2956 / 3.09					

Max Sizeable RPM = 3000 RPM. Table shown extended beyond this point for reference only.

Motor 186725/A01-ECM-50-277-16 has an rpm range of 1000 to 2390.

Motor 186725/A01-ECM-60-277-16 has an rpm range of 1000 to 2390.

Motor 186727/A01-ECM-50-480-16 has an rpm range of 1000 to 3000.

Motor 186727/A01-ECM-60-480-16 has an rpm range of 1000 to 3000.

Motor 186728/A01-ECM-50-240-16 has an rpm range of 1000 to 2770.

Motor 186728/A01-ECM-60-240-16 has an rpm range of 1000 to 2770.

Motor 186730/A01-ECM-60-240-18 has an rpm range of 1000 to 2700.