

RTU1-I.200-18-FA

CFM	Static Pressure in Inches W.G.								
	0.000	0.500	1.000	1.500	2.000	2.500	3.000	3.500	4.000
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
1100		817 / 0.18	1097 / 0.41	1321 / 0.69	1509 / 1.01	1672 / 1.35			
1290		848 / 0.21	1117 / 0.45	1337 / 0.74	1527 / 1.07	1693 / 1.43	1843 / 1.83	1975 / 2.23	2101 / 2.67
1480		882 / 0.24	1143 / 0.50	1357 / 0.80	1543 / 1.14	1711 / 1.51	1862 / 1.92	2000 / 2.35	2126 / 2.80
1670	640 / 0.09	917 / 0.28	1173 / 0.55	1380 / 0.86	1562 / 1.21	1727 / 1.60	1879 / 2.02	2017 / 2.46	2147 / 2.93
1860	713 / 0.12	953 / 0.31	1205 / 0.61	1407 / 0.94	1584 / 1.29	1745 / 1.69	1894 / 2.11	2033 / 2.57	
2050	785 / 0.16	991 / 0.35	1239 / 0.68	1438 / 1.02	1610 / 1.39	1767 / 1.79	1914 / 2.23	2050 / 2.69	
2240	858 / 0.21	1036 / 0.40	1274 / 0.74	1470 / 1.11	1639 / 1.49	1793 / 1.91	1936 / 2.35	2070 / 2.83	
2430	931 / 0.27	1085 / 0.46	1309 / 0.81	1504 / 1.20	1670 / 1.61	1820 / 2.03	1961 / 2.49	2091 / 2.97	
2620	1003 / 0.34	1139 / 0.52	1345 / 0.88	1538 / 1.30	1704 / 1.73	1852 / 2.18	1988 / 2.64		
2810	1076 / 0.42	1197 / 0.60	1384 / 0.96	1572 / 1.40	1737 / 1.85	1883 / 2.32	2019 / 2.81		
3000	1149 / 0.51	1258 / 0.70	1425 / 1.05	1608 / 1.50	1771 / 1.98	1917 / 2.48	2049 / 2.98		

Max Sizeable RPM = 2600 RPM. Table shown extended beyond this point for reference only.

Motor 00118ET3H143T-W22 has an rpm range of 600 to 1750.

Motor 00158ET3H145T-W22 has an rpm range of 600 to 1750.

Motor 00158OT3H145T-S has an rpm range of 600 to 1750.

Motor 00218ET3H145T-W22 has an rpm range of 600 to 1750.

Motor 00218OT3H145T-S has an rpm range of 600 to 1750.

Motor BMN145-2.0I2-CS-UB1-50 (1200RPM) has an rpm range of 600 to 1200.

Motor BMN145-2.0I2-CS-UB1-60 (1200RPM) has an rpm range of 600 to 1200.

Motor BMN145-2.0I2-ES-UB1-50 (1800RPM) has an rpm range of 600 to 1800.

Motor BMN145-2.0I2-ES-UB1-60 (1800RPM) has an rpm range of 600 to 1800.

Motor DHP0034 has an rpm range of 600 to 1750.

Motor DTP0014 has an rpm range of 600 to 1750.

Motor DTP0014-50HZ has an rpm range of 600 to 1429.

Motor DTP0016 has an rpm range of 600 to 1150.

Motor DTP0024 has an rpm range of 600 to 1740.

Motor DTP0024-50HZ has an rpm range of 600 to 1415.

Motor DTP0032 has an rpm range of 900 to 2600.

Motor DTP1/54 has an rpm range of 600 to 1750.

Motor DTP1/54-50HZ has an rpm range of 600 to 1426.

Motor GP0014 has an rpm range of 600 to 1800.

Motor GP0014-50 has an rpm range of 600 to 1440.

Motor GP0024 has an rpm range of 600 to 1740.

Motor GP0024-50 has an rpm range of 600 to 1440.

Motor GP1/54 has an rpm range of 600 to 1800.

Motor GP1/54-50 has an rpm range of 600 to 1440.

Motor GT0110 has an rpm range of 600 to 1770.