

# RTU1-I.200HE-15-FA

CFM	Static Pressure in Inches W.G.													
	0.000	0.250	0.500	0.750	1.000	1.250	1.500	1.750	2.000	2.250	2.500	2.750	3.000	3.250
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
1100		814 / 0.19	962 / 0.30	1111 / 0.44	1247 / 0.59	1370 / 0.75	1480 / 0.93	1583 / 1.11	1677 / 1.30	1763 / 1.48	1846 / 1.68	1926 / 1.89	2004 / 2.10	2075 / 2.32
1290		908 / 0.26	1032 / 0.38	1161 / 0.52	1287 / 0.68	1407 / 0.86	1518 / 1.05	1619 / 1.24	1713 / 1.44	1802 / 1.65	1886 / 1.87	1966 / 2.09	2041 / 2.31	2115 / 2.55
1480	902 / 0.24	1009 / 0.35	1115 / 0.48	1225 / 0.63	1338 / 0.79	1448 / 0.98	1555 / 1.18	1655 / 1.39	1749 / 1.60	1839 / 1.83	1922 / 2.05	2003 / 2.29	2079 / 2.53	2151 / 2.77
1670	1017 / 0.34	1113 / 0.47	1207 / 0.61	1302 / 0.76	1401 / 0.93	1500 / 1.12	1598 / 1.33	1694 / 1.54	1786 / 1.77	1874 / 2.01	1960 / 2.26	2039 / 2.51	2117 / 2.77	2189 / 3.02
1860	1133 / 0.48	1220 / 0.61	1303 / 0.76	1388 / 0.92	1475 / 1.10	1563 / 1.29	1653 / 1.51	1742 / 1.73	1829 / 1.97	1914 / 2.21	1996 / 2.47	2076 / 2.74	2153 / 3.01	
2050	1248 / 0.64	1328 / 0.79	1404 / 0.95	1480 / 1.12	1558 / 1.30	1636 / 1.50	1717 / 1.72	1798 / 1.95	1879 / 2.19	1960 / 2.45	2038 / 2.71	2116 / 2.99	2190 / 3.27	
2240	1364 / 0.83	1437 / 0.99	1506 / 1.17	1576 / 1.35	1647 / 1.54	1718 / 1.75	1791 / 1.97	1864 / 2.20	1938 / 2.44	2013 / 2.71	2086 / 2.98	2160 / 3.26		
2430	1480 / 1.06	1548 / 1.24	1612 / 1.42	1676 / 1.61	1741 / 1.82	1805 / 2.03	1871 / 2.25	1938 / 2.49	2007 / 2.75	2073 / 3.01	2143 / 3.29			
2620	1596 / 1.33	1658 / 1.52	1719 / 1.72	1779 / 1.92	1837 / 2.13	1897 / 2.35	1958 / 2.59	2018 / 2.83	2081 / 3.09	2142 / 3.35				
2810	1711 / 1.64	1770 / 1.84	1827 / 2.06	1882 / 2.27	1938 / 2.50	1993 / 2.72	2050 / 2.97	2105 / 3.22	2163 / 3.48					
3000	1827 / 1.99	1882 / 2.21	1935 / 2.44	1988 / 2.67	2039 / 2.90	2092 / 3.14	2143 / 3.39	2196 / 3.65						

Max Sizeable RPM = 2200 RPM. Table shown extended beyond this point for reference only.

Motor 00118ET3H143T-W22 has an rpm range of 800 to 1750.

Motor 00118OT3H143T-S has an rpm range of 800 to 1750.

Motor 00158ET3H145T-W22 has an rpm range of 800 to 1750.

Motor 00158OT3H145T-S has an rpm range of 800 to 1750.

Motor 00212OT3H184T-S has an rpm range of 800 to 1150.

Motor 00218ET3H145T-W22 has an rpm range of 800 to 1750.

Motor 00218OT3H145T-S has an rpm range of 800 to 1750.

Motor 00536OT3H182T-S has an rpm range of 900 to 2200.

Motor BMN145-2.0I2-CS-UB1-50 (1200RPM) has an rpm range of 800 to 1200.

Motor BMN145-2.0I2-CS-UB1-60 (1200RPM) has an rpm range of 800 to 1200.

Motor BMN145-2.0I2-ES-UB1-50 (1800RPM) has an rpm range of 800 to 1800.

Motor BMN145-2.0I2-ES-UB1-60 (1800RPM) has an rpm range of 800 to 1800.

Motor DTP0014 has an rpm range of 800 to 1750.

Motor DTP0014-50HZ has an rpm range of 800 to 1429.

Motor DTP0016 has an rpm range of 800 to 1150.

Motor DTP0022 has an rpm range of 900 to 2200.

Motor DTP0024 has an rpm range of 800 to 1740.

Motor DTP0024-50HZ has an rpm range of 800 to 1415.

Motor DTP0032 has an rpm range of 900 to 2200.

Motor DTP0034 has an rpm range of 800 to 1755.

Motor DTP0034-50HZ has an rpm range of 800 to 1438.

Motor DTP0054 has an rpm range of 800 to 1750.

Motor DTP0054-50 has an rpm range of 800 to 1435.

Motor DTP1/54 has an rpm range of 800 to 1750.

Motor DTP1/54-50HZ has an rpm range of 800 to 1426.

Motor GP0014 has an rpm range of 800 to 1800.

Motor GP0014-50 has an rpm range of 800 to 1440.

Motor GP0024 has an rpm range of 800 to 1740.

Motor GP0024-50 has an rpm range of 800 to 1440.

Motor GP1/54 has an rpm range of 800 to 1800.

Motor GP1/54-50 has an rpm range of 800 to 1440.

Motor NP0024 has an rpm range of 800 to 1740.