

# RTU1-I.200HE-16-FA

CFM	Static Pressure in Inches W.G.											
	0.000	0.500	1.000	1.500	2.000	2.500	3.000	3.500	4.000	4.500	5.000	5.500
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
1100		1179 / 0.20	1419 / 0.35	1632 / 0.52	1821 / 0.69	1996 / 0.88	2157 / 1.07	2306 / 1.27	2450 / 1.48	2588 / 1.70	2716 / 1.93	2842 / 2.16
1290	1065 / 0.13	1298 / 0.26	1516 / 0.43	1713 / 0.62	1891 / 0.81	2057 / 1.01	2213 / 1.22	2358 / 1.44	2495 / 1.66	2627 / 1.90	2756 / 2.15	2873 / 2.38
1480	1222 / 0.19	1424 / 0.34	1623 / 0.53	1805 / 0.73	1973 / 0.94	2129 / 1.16	2277 / 1.39	2418 / 1.62	2552 / 1.87	2676 / 2.11	2803 / 2.38	2919 / 2.64
1670	1379 / 0.27	1558 / 0.44	1736 / 0.64	1906 / 0.86	2064 / 1.09	2212 / 1.33	2355 / 1.58	2489 / 1.83	2618 / 2.09	2738 / 2.35	2860 / 2.64	2972 / 2.91
1860	1535 / 0.38	1696 / 0.55	1858 / 0.77	2015 / 1.01	2158 / 1.25	2305 / 1.51	2438 / 1.78	2566 / 2.05	2688 / 2.33	2810 / 2.62	2925 / 2.91	
2050	1691 / 0.51	1837 / 0.70	1985 / 0.92	2129 / 1.17	2270 / 1.45	2403 / 1.72	2531 / 2.01	2652 / 2.29	2770 / 2.59	2883 / 2.89	2993 / 3.20	
2240	1845 / 0.66	1981 / 0.86	2117 / 1.11	2251 / 1.37	2378 / 1.65	2508 / 1.95	2629 / 2.25	2745 / 2.56	2861 / 2.89	2967 / 3.20		
2430	2005 / 0.84	2128 / 1.06	2252 / 1.31	2378 / 1.60	2500 / 1.90	2619 / 2.21	2733 / 2.53	2845 / 2.86	2953 / 3.19			
2620	2162 / 1.06	2274 / 1.29	2391 / 1.56	2507 / 1.85	2620 / 2.16	2732 / 2.49	2842 / 2.82	2950 / 3.18				
2810	2318 / 1.30	2425 / 1.55	2532 / 1.83	2638 / 2.13	2747 / 2.46	2853 / 2.80	2958 / 3.16					
3000	2475 / 1.59	2573 / 1.84	2674 / 2.14	2775 / 2.46	2876 / 2.80	2976 / 3.15						

Max Sizeable RPM = 3000 RPM. Table shown extended beyond this point for reference only.

Motor 186725/A01-ECM-50-277-16 has an rpm range of 1000 to 2390.

Motor 186725/A01-ECM-60-277-16 has an rpm range of 1000 to 2390.

Motor 186727/A01-ECM-50-480-16 has an rpm range of 1000 to 3000.

Motor 186727/A01-ECM-60-480-16 has an rpm range of 1000 to 3000.

Motor 186728/A01-ECM-50-240-16 has an rpm range of 1000 to 2770.

Motor 186728/A01-ECM-60-240-16 has an rpm range of 1000 to 2770.

Motor 186730/A01-ECM-60-240-18 has an rpm range of 1000 to 2700.