

RTU1-I.200HE-18-FA

CFM	Static Pressure in Inches W.G.											
	0.000	0.500	1.000	1.500	2.000	2.500	3.000	3.500	4.000	4.500	5.000	5.500
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
1100			1247 / 0.41	1459 / 0.62	1644 / 0.84	1812 / 1.08	1964 / 1.33	2107 / 1.60	2240 / 1.87	2366 / 2.16	2489 / 2.46	2600 / 2.76
1290		1076 / 0.29	1308 / 0.50	1511 / 0.73	1691 / 0.97	1853 / 1.23	2003 / 1.50	2143 / 1.79	2275 / 2.08	2398 / 2.38	2515 / 2.70	2627 / 3.02
1480		1164 / 0.36	1378 / 0.59	1569 / 0.85	1741 / 1.11	1900 / 1.39	2044 / 1.68	2183 / 1.99	2309 / 2.29	2434 / 2.63	2547 / 2.95	2662 / 3.31
1670	1062 / 0.25	1259 / 0.45	1455 / 0.71	1636 / 0.98	1800 / 1.27	1951 / 1.57	2093 / 1.88	2227 / 2.20	2352 / 2.54	2470 / 2.88	2585 / 3.23	2698 / 3.61
1860	1182 / 0.34	1359 / 0.57	1537 / 0.84	1706 / 1.13	1864 / 1.44	2011 / 1.77	2148 / 2.10	2277 / 2.44	2400 / 2.80	2517 / 3.16	2627 / 3.53	
2050	1303 / 0.46	1462 / 0.70	1626 / 0.99	1784 / 1.30	1932 / 1.63	2073 / 1.98	2207 / 2.34	2332 / 2.70	2452 / 3.08	2566 / 3.46	2676 / 3.86	
2240	1424 / 0.60	1569 / 0.86	1719 / 1.16	1867 / 1.50	2007 / 1.85	2141 / 2.21	2270 / 2.59	2391 / 2.98	2508 / 3.38	2620 / 3.79		
2430	1545 / 0.76	1678 / 1.04	1816 / 1.36	1953 / 1.71	2086 / 2.08	2215 / 2.48	2337 / 2.87	2455 / 3.28	2569 / 3.71	2676 / 4.13		
2620	1666 / 0.96	1788 / 1.25	1917 / 1.59	2044 / 1.96	2171 / 2.35	2292 / 2.76	2410 / 3.18	2522 / 3.61	2631 / 4.05			
2810	1786 / 1.18	1900 / 1.49	2019 / 1.85	2139 / 2.23	2257 / 2.64	2373 / 3.07	2485 / 3.51	2595 / 3.97	2699 / 4.43			
3000	1907 / 1.44	2013 / 1.77	2125 / 2.14	2237 / 2.54	2347 / 2.96	2459 / 3.42	2566 / 3.88	2671 / 4.36				

Max Sizeable RPM = 2700 RPM. Table shown extended beyond this point for reference only.

Motor 186726/A01-ECM-50-277-18 has an rpm range of 1000 to 1950.

Motor 186726/A01-ECM-60-277-18 has an rpm range of 1000 to 1950.

Motor 186730/A01-ECM-50-240-18 has an rpm range of 1000 to 2700.

Motor 186730/A01-ECM-60-240-18 has an rpm range of 1000 to 2700.

Motor 186731/A01-ECM-50-480-18 has an rpm range of 1000 to 2700.

Motor 186731/A01-ECM-60-480-18 has an rpm range of 1000 to 2700.