

RTU1-I.50-16-FA

CFM	Static Pressure in Inches W.G.												
	0.000	0.500	1.000	1.500	2.000	2.500	3.000	3.500	4.000	4.500	5.000	5.500	6.000
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
500			1235 / 0.18	1488 / 0.29	1706 / 0.42	1901 / 0.56	2075 / 0.70	2232 / 0.85	2381 / 1.01	2525 / 1.18	2660 / 1.35	2778 / 1.51	2907 / 1.70
750		1040 / 0.14	1318 / 0.25	1550 / 0.38	1756 / 0.53	1943 / 0.69	2113 / 0.86	2273 / 1.04	2419 / 1.22	2560 / 1.42	2688 / 1.61	2820 / 1.83	2941 / 2.04
1000		1195 / 0.21	1439 / 0.36	1650 / 0.51	1838 / 0.68	2012 / 0.85	2174 / 1.04	2326 / 1.24	2469 / 1.44	2604 / 1.66	2732 / 1.88	2857 / 2.11	2976 / 2.35
1250	1143 / 0.17	1369 / 0.32	1584 / 0.49	1776 / 0.68	1950 / 0.87	2111 / 1.06	2260 / 1.27	2404 / 1.48	2541 / 1.71	2671 / 1.94	2796 / 2.18	2914 / 2.43	
1500	1370 / 0.29	1559 / 0.46	1746 / 0.66	1921 / 0.88	2080 / 1.10	2232 / 1.32	2373 / 1.55	2508 / 1.79	2636 / 2.04	2757 / 2.28	2874 / 2.54	2988 / 2.80	
1750	1598 / 0.46	1759 / 0.65	1923 / 0.88	2081 / 1.12	2226 / 1.37	2368 / 1.63	2500 / 1.89	2628 / 2.15	2747 / 2.42	2864 / 2.69	2976 / 2.97		
2000	1826 / 0.69	1967 / 0.90	2110 / 1.14	2252 / 1.42	2389 / 1.70	2519 / 1.98	2642 / 2.27	2762 / 2.57	2878 / 2.87	2985 / 3.16			
2250	2055 / 0.99	2178 / 1.21	2308 / 1.48	2435 / 1.77	2560 / 2.08	2679 / 2.39	2795 / 2.71	2907 / 3.04					
2500	2283 / 1.35	2395 / 1.60	2508 / 1.88	2623 / 2.20	2738 / 2.53	2851 / 2.88	2959 / 3.22						
2750	2511 / 1.80	2612 / 2.07	2715 / 2.37	2821 / 2.70	2922 / 3.05								
3000	2740 / 2.34	2833 / 2.63	2927 / 2.95										

Max Sizeable RPM = 3000 RPM. Table shown extended beyond this point for reference only.

Motor 186725/A01-ECM-50-277-16 has an rpm range of 1000 to 2390.

Motor 186725/A01-ECM-60-277-16 has an rpm range of 1000 to 2390.

Motor 186727/A01-ECM-50-480-16 has an rpm range of 1000 to 3000.

Motor 186727/A01-ECM-60-480-16 has an rpm range of 1000 to 3000.

Motor 186728/A01-ECM-50-240-16 has an rpm range of 1000 to 2770.

Motor 186728/A01-ECM-60-240-16 has an rpm range of 1000 to 2770.

Motor 186730/A01-ECM-60-240-18 has an rpm range of 1000 to 2700.