

RTU1-I.50-18-FA

CFM	Static Pressure in Inches W.G.												
	0.000	0.500	1.000	1.500	2.000	2.500	3.000	3.500	4.000	4.500	5.000	5.500	6.000
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
500			1131 / 0.23	1362 / 0.38	1562 / 0.54	1736 / 0.72	1894 / 0.91	2041 / 1.12	2183 / 1.35	2304 / 1.56	2427 / 1.80	2538 / 2.03	2646 / 2.28
750		923 / 0.16	1194 / 0.31	1415 / 0.49	1606 / 0.68	1777 / 0.88	1938 / 1.11	2083 / 1.34	2219 / 1.59	2344 / 1.84	2467 / 2.11	2577 / 2.37	2688 / 2.66
1000		1035 / 0.24	1282 / 0.43	1488 / 0.63	1669 / 0.84	1835 / 1.07	1988 / 1.32	2128 / 1.58	2262 / 1.85	2387 / 2.13	2506 / 2.42	2618 / 2.72	
1250	910 / 0.17	1164 / 0.36	1386 / 0.57	1578 / 0.80	1751 / 1.05	1908 / 1.31	2053 / 1.58	2189 / 1.86	2319 / 2.16	2441 / 2.47	2556 / 2.78	2665 / 3.10	
1500	1092 / 0.29	1305 / 0.51	1506 / 0.76	1685 / 1.03	1845 / 1.30	1995 / 1.59	2134 / 1.88	2266 / 2.20	2389 / 2.52	2504 / 2.84	2618 / 3.18		
1750	1274 / 0.46	1457 / 0.71	1636 / 0.99	1800 / 1.29	1953 / 1.60	2093 / 1.92	2226 / 2.25	2352 / 2.59	2468 / 2.93	2585 / 3.30	2692 / 3.66		
2000	1456 / 0.69	1616 / 0.97	1776 / 1.28	1929 / 1.62	2070 / 1.96	2203 / 2.31	2328 / 2.67	2448 / 3.04	2564 / 3.42	2670 / 3.80			
2250	1638 / 0.99	1779 / 1.29	1923 / 1.64	2062 / 2.00	2195 / 2.38	2322 / 2.76	2435 / 3.14	2554 / 3.55	2663 / 3.96				
2500	1820 / 1.35	1946 / 1.69	2076 / 2.06	2205 / 2.46	2328 / 2.86	2446 / 3.28	2559 / 3.71	2668 / 4.15					
2750	2001 / 1.80	2115 / 2.16	2234 / 2.56	2352 / 2.99	2466 / 3.43	2577 / 3.88	2686 / 4.35						
3000	2183 / 2.34	2288 / 2.73	2396 / 3.16	2504 / 3.61	2611 / 4.09								

Max Sizeable RPM = 2700 RPM. Table shown extended beyond this point for reference only.

Motor 186726/A01-ECM-50-277-18 has an rpm range of 900 to 1950.

Motor 186726/A01-ECM-60-277-18 has an rpm range of 900 to 1950.

Motor 186730/A01-ECM-50-240-18 has an rpm range of 900 to 2700.

Motor 186730/A01-ECM-60-240-18 has an rpm range of 900 to 2700.

Motor 186731/A01-ECM-50-480-18 has an rpm range of 900 to 2700.

Motor 186731/A01-ECM-60-480-18 has an rpm range of 900 to 2700.