

# RTU1-I.50HE-13-FA

CFM	Static Pressure in Inches W.G.												
	0.000	0.250	0.500	0.750	1.000	1.250	1.500	1.750	2.000	2.250	2.500	2.750	3.000
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
500			1018 / 0.18	1205 / 0.27	1370 / 0.39	1515 / 0.51	1645 / 0.63	1767 / 0.77	1880 / 0.92	1992 / 1.09	2092 / 1.25	2183 / 1.41	2283 / 1.61
670		904 / 0.14	1104 / 0.24	1274 / 0.35	1426 / 0.47	1565 / 0.61	1692 / 0.74	1811 / 0.89	1925 / 1.05	2030 / 1.22	2134 / 1.39	2226 / 1.57	
840		1031 / 0.21	1207 / 0.33	1361 / 0.45	1503 / 0.59	1634 / 0.74	1754 / 0.89	1867 / 1.05	1976 / 1.22	2079 / 1.39	2176 / 1.57	2270 / 1.76	
1010	1017 / 0.20	1170 / 0.30	1324 / 0.43	1466 / 0.58	1596 / 0.73	1718 / 0.90	1833 / 1.07	1939 / 1.24	2045 / 1.42	2140 / 1.61	2235 / 1.80		
1180	1187 / 0.31	1317 / 0.43	1451 / 0.58	1582 / 0.74	1700 / 0.91	1815 / 1.09	1922 / 1.27	2024 / 1.46	2122 / 1.66	2214 / 1.86			
1350	1358 / 0.47	1471 / 0.60	1588 / 0.76	1705 / 0.93	1817 / 1.12	1923 / 1.32	2024 / 1.52	2119 / 1.72	2213 / 1.94	2300 / 2.15			
1520	1529 / 0.67	1629 / 0.81	1733 / 0.98	1838 / 1.17	1939 / 1.37	2038 / 1.58	2132 / 1.80	2225 / 2.03					
1690	1700 / 0.91	1788 / 1.07	1882 / 1.25	1977 / 1.46	2071 / 1.67	2161 / 1.90	2250 / 2.13						
1860	1871 / 1.22	1952 / 1.39	2035 / 1.58	2121 / 1.80	2206 / 2.03	2291 / 2.26							
2030	2042 / 1.58	2115 / 1.77	2192 / 1.98	2271 / 2.20									
2200	2213 / 2.02	2280 / 2.21											

Max Sizeable RPM = 2300 RPM. Table shown extended beyond this point for reference only.

Motor 00118ET3H143T-W22 has an rpm range of 900 to 1750.

Motor 00118OT3H143T-S has an rpm range of 900 to 1750.

Motor 00158ET3H145T-W22 has an rpm range of 900 to 1750.

Motor 00158OT3H145T-S has an rpm range of 900 to 1750.

Motor 00218ET3H145T-W22 has an rpm range of 900 to 1750.

Motor 00218OT3H145T-S has an rpm range of 900 to 1750.

Motor BMN145-2.0I2-CS-UB1-50 (1200RPM) has an rpm range of 900 to 1200.

Motor BMN145-2.0I2-CS-UB1-60 (1200RPM) has an rpm range of 900 to 1200.

Motor BMN145-2.0I2-ES-UB1-50 (1800RPM) has an rpm range of 900 to 1800.

Motor BMN145-2.0I2-ES-UB1-60 (1800RPM) has an rpm range of 900 to 1800.

Motor DTP0014 has an rpm range of 900 to 1750.

Motor DTP0014-50HZ has an rpm range of 900 to 1429.

Motor DTP0016 has an rpm range of 900 to 1150.

Motor DTP0022 has an rpm range of 900 to 2300.

Motor DTP0024 has an rpm range of 900 to 1740.

Motor DTP0024-50HZ has an rpm range of 900 to 1415.

Motor DTP0032 has an rpm range of 900 to 2300.

Motor DTP1/54 has an rpm range of 900 to 1750.

Motor DTP1/54-50HZ has an rpm range of 900 to 1426.

Motor GP0014 has an rpm range of 900 to 1800.

Motor GP0014-50 has an rpm range of 900 to 1440.

Motor GP0024 has an rpm range of 900 to 1740.

Motor GP0024-50 has an rpm range of 900 to 1440.

Motor GP1/54 has an rpm range of 900 to 1800.

Motor GP1/54-50 has an rpm range of 900 to 1440.