

RTU1-I.75-16-FA

CFM	Static Pressure in Inches W.G.												
	0.000	0.500	1.000	1.500	2.000	2.500	3.000	3.500	4.000	4.500	5.000	5.500	6.000
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
500			1222 / 0.18	1479 / 0.29	1695 / 0.41	1887 / 0.55	2066 / 0.69	2222 / 0.84	2381 / 1.01	2513 / 1.16	2646 / 1.32	2778 / 1.51	2890 / 1.67
750		1007 / 0.13	1291 / 0.24	1527 / 0.37	1736 / 0.52	1923 / 0.67	2095 / 0.84	2252 / 1.01	2404 / 1.20	2542 / 1.39	2679 / 1.60	2809 / 1.81	2930 / 2.02
1000		1143 / 0.19	1395 / 0.33	1610 / 0.48	1802 / 0.64	1980 / 0.82	2146 / 1.01	2299 / 1.20	2445 / 1.41	2577 / 1.61	2710 / 1.84	2833 / 2.06	2959 / 2.31
1250	1063 / 0.13	1299 / 0.27	1523 / 0.44	1719 / 0.62	1897 / 0.81	2063 / 1.00	2216 / 1.21	2363 / 1.42	2500 / 1.64	2632 / 1.87	2759 / 2.11	2880 / 2.36	2998 / 2.61
1500	1276 / 0.23	1472 / 0.38	1669 / 0.57	1847 / 0.78	2013 / 1.00	2168 / 1.22	2311 / 1.45	2447 / 1.68	2582 / 1.93	2703 / 2.17	2825 / 2.43	2941 / 2.69	
1750	1488 / 0.36	1656 / 0.52	1827 / 0.74	1989 / 0.98	2142 / 1.22	2288 / 1.48	2424 / 1.73	2551 / 1.99	2676 / 2.26	2796 / 2.53	2912 / 2.81		
2000	1701 / 0.53	1845 / 0.71	1996 / 0.95	2144 / 1.21	2286 / 1.48	2418 / 1.76	2548 / 2.05	2670 / 2.34	2789 / 2.64	2903 / 2.93			
2250	1913 / 0.76	2040 / 0.95	2176 / 1.21	2308 / 1.48	2438 / 1.78	2563 / 2.09	2685 / 2.41	2799 / 2.72	2911 / 3.05				
2500	2124 / 1.04	2240 / 1.25	2361 / 1.52	2480 / 1.81	2599 / 2.13	2717 / 2.47	2828 / 2.81	2938 / 3.16					
2750	2336 / 1.38	2442 / 1.62	2549 / 1.89	2660 / 2.20	2769 / 2.54	2877 / 2.89	2983 / 3.26						
3000	2549 / 1.80	2646 / 2.04	2745 / 2.34	2844 / 2.66	2944 / 3.01								

Max Sizeable RPM = 3000 RPM. Table shown extended beyond this point for reference only.

Motor 186725/A01-ECM-50-277-16 has an rpm range of 1000 to 2390.

Motor 186725/A01-ECM-60-277-16 has an rpm range of 1000 to 2390.

Motor 186727/A01-ECM-50-480-16 has an rpm range of 1000 to 3000.

Motor 186727/A01-ECM-60-480-16 has an rpm range of 1000 to 3000.

Motor 186728/A01-ECM-50-240-16 has an rpm range of 1000 to 2770.

Motor 186728/A01-ECM-60-240-16 has an rpm range of 1000 to 2770.

Motor 186730/A01-ECM-60-240-18 has an rpm range of 1000 to 2700.