

RTU1-I.75HE-18-FA

CFM	Static Pressure in Inches W.G.												
	0.000	0.500	1.000	1.500	2.000	2.500	3.000	3.500	4.000	4.500	5.000	5.500	6.000
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
500			1121 / 0.23	1355 / 0.37	1553 / 0.54	1730 / 0.72	1887 / 0.91	2033 / 1.11	2174 / 1.33	2304 / 1.56	2427 / 1.80	2538 / 2.03	2646 / 2.28
750			1176 / 0.30	1399 / 0.47	1592 / 0.66	1765 / 0.87	1923 / 1.09	2066 / 1.31	2206 / 1.57	2329 / 1.81	2451 / 2.08	2568 / 2.36	2679 / 2.64
1000		994 / 0.22	1248 / 0.40	1460 / 0.60	1647 / 0.81	1815 / 1.04	1969 / 1.29	2110 / 1.54	2242 / 1.81	2370 / 2.09	2488 / 2.38	2604 / 2.68	
1250		1109 / 0.31	1338 / 0.52	1538 / 0.75	1715 / 0.99	1874 / 1.25	2023 / 1.51	2163 / 1.80	2294 / 2.09	2413 / 2.39	2530 / 2.70	2643 / 3.03	
1500	1018 / 0.23	1239 / 0.44	1444 / 0.68	1627 / 0.94	1794 / 1.21	1948 / 1.49	2089 / 1.78	2226 / 2.10	2351 / 2.41	2471 / 2.74	2586 / 3.08	2693 / 3.42	
1750	1186 / 0.36	1377 / 0.60	1560 / 0.87	1729 / 1.16	1886 / 1.46	2030 / 1.77	2169 / 2.10	2297 / 2.43	2417 / 2.77	2536 / 3.14	2648 / 3.50		
2000	1356 / 0.54	1523 / 0.80	1686 / 1.10	1842 / 1.42	1988 / 1.76	2125 / 2.10	2255 / 2.46	2378 / 2.82	2497 / 3.20	2608 / 3.57			
2250	1525 / 0.77	1674 / 1.06	1820 / 1.38	1963 / 1.73	2099 / 2.10	2228 / 2.47	2351 / 2.86	2470 / 3.26	2583 / 3.67	2691 / 4.08			
2500	1695 / 1.06	1829 / 1.37	1962 / 1.73	2092 / 2.10	2218 / 2.50	2339 / 2.90	2456 / 3.32	2569 / 3.76	2677 / 4.19				
2750	1864 / 1.41	1986 / 1.75	2107 / 2.13	2227 / 2.53	2344 / 2.96	2458 / 3.39	2568 / 3.84	2675 / 4.31					
3000	2034 / 1.84	2144 / 2.20	2257 / 2.60	2368 / 3.03	2477 / 3.49	2584 / 3.96	2686 / 4.43						

Max Sizeable RPM = 2700 RPM. Table shown extended beyond this point for reference only.

Motor 186726/A01-ECM-50-277-18 has an rpm range of 900 to 1950.

Motor 186726/A01-ECM-60-277-18 has an rpm range of 900 to 1950.

Motor 186730/A01-ECM-50-240-18 has an rpm range of 900 to 2700.

Motor 186730/A01-ECM-60-240-18 has an rpm range of 900 to 2700.

Motor 186731/A01-ECM-50-480-18 has an rpm range of 900 to 2700.

Motor 186731/A01-ECM-60-480-18 has an rpm range of 900 to 2700.