

RTU2-E.156-11-FA

CFM	Static Pressure in Inches W.G.									
	0.000	0.250	0.500	0.750	1.000	1.250	1.500	1.750	2.000	2.250
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
850			1489 / 0.29	1628 / 0.39	1753 / 0.49	1872 / 0.59	1986 / 0.70	2094 / 0.82	2202 / 0.94	2304 / 1.07
940		1424 / 0.24	1585 / 0.35	1718 / 0.46	1840 / 0.57	1950 / 0.67	2057 / 0.79	2161 / 0.91	2260 / 1.03	2356 / 1.16
1030		1526 / 0.29	1680 / 0.41	1813 / 0.53	1929 / 0.65	2036 / 0.77	2137 / 0.89	2234 / 1.01	2330 / 1.14	
1120	1456 / 0.24	1630 / 0.35	1781 / 0.48	1908 / 0.61	2022 / 0.74	2125 / 0.87	2222 / 1.00	2314 / 1.13		
1210	1573 / 0.31	1736 / 0.42	1879 / 0.56	2003 / 0.70	2115 / 0.84	2216 / 0.98	2309 / 1.12			
1300	1691 / 0.38	1841 / 0.50	1982 / 0.65	2100 / 0.80	2211 / 0.96	2309 / 1.10	2399 / 1.25			
1390	1808 / 0.46	1950 / 0.59	2084 / 0.75	2199 / 0.91	2305 / 1.07					
1480	1925 / 0.56	2058 / 0.69	2186 / 0.86	2302 / 1.03						
1570	2042 / 0.67	2169 / 0.81	2289 / 0.98							
1660	2159 / 0.79	2277 / 0.93	2395 / 1.11							
1750	2276 / 0.92	2387 / 1.07								

Max Sizeable RPM = 2400 RPM. Table shown extended beyond this point for reference only.

- Motor 00118ET3H143T-W22 has an rpm range of 1400 to 1750.
- Motor 00118OT3H143T-S has an rpm range of 1400 to 1750.
- Motor 00158ET3H145T-W22 has an rpm range of 1400 to 1750.
- Motor 00158OT3H145T-S has an rpm range of 1400 to 1750.
- Motor 00218ET3H145T-W22 has an rpm range of 1400 to 1750.
- Motor 00218OT3H145T-S has an rpm range of 1400 to 1750.
- Motor 00318OT3E56Z-48PP has an rpm range of 1400 to 1730.

- Motor BMN145-2.0I2-ES-UB1-50 (1800RPM) has an rpm range of 1400 to 1800.
- Motor BMN145-2.0I2-ES-UB1-60 (1800RPM) has an rpm range of 1400 to 1800.
- Motor DTP0014 has an rpm range of 1400 to 1750.
- Motor DTP0014-50HZ has an rpm range of 1400 to 1429.
- Motor DTP0022 has an rpm range of 1400 to 2400.
- Motor DTP0024 has an rpm range of 1400 to 1740.
- Motor DTP0024-50HZ has an rpm range of 1400 to 1415.
- Motor DTP0032 has an rpm range of 1400 to 2400.
- Motor DTP1/54 has an rpm range of 1400 to 1750.
- Motor DTP1/54-50HZ has an rpm range of 1400 to 1426.
- Motor GP0014 has an rpm range of 1400 to 1800.
- Motor GP0014-50 has an rpm range of 1400 to 1440.
- Motor GP0022 has an rpm range of 1400 to 2400.
- Motor GP0024 has an rpm range of 1400 to 1740.
- Motor GP0024-50 has an rpm range of 1400 to 1440.
- Motor GP1/54 has an rpm range of 1400 to 1800.
- Motor GP1/54-50 has an rpm range of 1400 to 1440.