

RTU2-E.306-15-FA

CFM	Static Pressure in Inches W.G.													
	0.000	0.250	0.500	0.750	1.000	1.250	1.500	1.750	2.000	2.250	2.500	2.750	3.000	3.250
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
1100				1016 / 0.34	1157 / 0.49	1287 / 0.64	1405 / 0.81	1513 / 0.98	1613 / 1.17	1708 / 1.36	1797 / 1.56	1880 / 1.76	1961 / 1.97	2037 / 2.19
1400			958 / 0.30	1075 / 0.43	1193 / 0.57	1308 / 0.73	1420 / 0.91	1527 / 1.10	1626 / 1.30	1722 / 1.51	1811 / 1.72	1897 / 1.95	1980 / 2.19	2056 / 2.42
1700		973 / 0.29	1073 / 0.41	1168 / 0.55	1265 / 0.70	1362 / 0.86	1458 / 1.04	1554 / 1.24	1647 / 1.45	1738 / 1.67	1826 / 1.89	1910 / 2.13	1993 / 2.38	2071 / 2.64
2000	974 / 0.27	1109 / 0.42	1198 / 0.56	1281 / 0.71	1362 / 0.87	1444 / 1.04	1526 / 1.22	1609 / 1.42	1691 / 1.63	1773 / 1.86	1854 / 2.09	1932 / 2.34	2010 / 2.59	2086 / 2.85
2300	1120 / 0.41	1247 / 0.59	1329 / 0.75	1404 / 0.91	1475 / 1.08	1547 / 1.26	1617 / 1.46	1689 / 1.66	1760 / 1.87	1831 / 2.10	1902 / 2.34	1974 / 2.59	2046 / 2.85	2116 / 3.12
2600	1266 / 0.59	1387 / 0.80	1464 / 0.98	1533 / 1.16	1598 / 1.35	1661 / 1.54	1724 / 1.74	1786 / 1.95	1849 / 2.18	1912 / 2.41	1976 / 2.65	2039 / 2.91	2102 / 3.17	2165 / 3.44
2900	1413 / 0.82	1527 / 1.07	1600 / 1.27	1666 / 1.47	1725 / 1.67	1784 / 1.88	1840 / 2.09	1897 / 2.31	1953 / 2.54	2008 / 2.78	2066 / 3.03	2121 / 3.29	2177 / 3.55	
3200	1559 / 1.11	1668 / 1.38	1739 / 1.61	1801 / 1.83	1857 / 2.05	1910 / 2.27	1963 / 2.50	2015 / 2.74	2066 / 2.98	2118 / 3.23	2168 / 3.49			
3500	1705 / 1.45	1810 / 1.76	1879 / 2.01	1937 / 2.25	1991 / 2.49	2042 / 2.73	2091 / 2.98	2139 / 3.23	2186 / 3.48					
3800	1851 / 1.85	1952 / 2.19	2018 / 2.47	2074 / 2.74	2126 / 3.00	2175 / 3.26								
4100	1997 / 2.33	2094 / 2.70	2159 / 3.01											

Max Sizeable RPM = 2200 RPM. Table shown extended beyond this point for reference only.

Motor 00158ET3H145T-W22 has an rpm range of 900 to 1750.

Motor 00158OT3H145T-S has an rpm range of 900 to 1750.

Motor 00218ET3H145T-W22 has an rpm range of 900 to 1750.

Motor 00218OT3H145T-S has an rpm range of 900 to 1750.

Motor 00318ET3H182T-W22 has an rpm range of 900 to 1750.

Motor 00318OT3H182T-S has an rpm range of 900 to 1750.

Motor 00536OT3H182T-S has an rpm range of 900 to 2200.

Motor BMN145-2.0I2-CS-UB1-50 (1200RPM) has an rpm range of 900 to 1200.

Motor BMN145-2.0I2-CS-UB1-60 (1200RPM) has an rpm range of 900 to 1200.

Motor BMN145-2.0I2-ES-UB1-50 (1800RPM) has an rpm range of 900 to 1800.

Motor BMN145-2.0I2-ES-UB1-60 (1800RPM) has an rpm range of 900 to 1800.

Motor DTP0022 has an rpm range of 900 to 2200.

Motor DTP0024 has an rpm range of 900 to 1740.

Motor DTP0024-50HZ has an rpm range of 900 to 1415.

Motor DTP0032 has an rpm range of 900 to 2200.

Motor DTP0054 has an rpm range of 900 to 1750.

Motor DTP0054-50 has an rpm range of 900 to 1435.

Motor DTP1/54 has an rpm range of 900 to 1750.

Motor DTP1/54-50HZ has an rpm range of 900 to 1426.

Motor GP0024 has an rpm range of 900 to 1740.

Motor GP0024-50 has an rpm range of 900 to 1440.

Motor GP1/54 has an rpm range of 900 to 1800.

Motor GP1/54-50 has an rpm range of 900 to 1440.

Motor NP0024 has an rpm range of 900 to 1740.