

RTU2-E.456-15-FA

CFM	Static Pressure in Inches W.G.													
	0.000	0.250	0.500	0.750	1.000	1.250	1.500	1.750	2.000	2.250	2.500	2.750	3.000	3.250
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
1500			995 / 0.34	1104 / 0.46	1214 / 0.61	1323 / 0.77	1430 / 0.95	1534 / 1.14	1632 / 1.35	1726 / 1.56	1816 / 1.78	1901 / 2.01	1984 / 2.25	2060 / 2.49
1790		1014 / 0.33	1110 / 0.45	1201 / 0.59	1292 / 0.74	1383 / 0.91	1476 / 1.09	1567 / 1.29	1657 / 1.50	1746 / 1.72	1832 / 1.95	1916 / 2.19	1996 / 2.44	2074 / 2.70
2080	1013 / 0.30	1145 / 0.46	1233 / 0.61	1313 / 0.76	1391 / 0.92	1470 / 1.09	1549 / 1.28	1628 / 1.48	1706 / 1.69	1785 / 1.91	1864 / 2.15	1942 / 2.40	2017 / 2.65	2093 / 2.92
2370	1154 / 0.45	1279 / 0.64	1361 / 0.80	1434 / 0.97	1504 / 1.14	1573 / 1.32	1641 / 1.52	1710 / 1.72	1779 / 1.94	1849 / 2.17	1917 / 2.40	1988 / 2.66	2056 / 2.91	2126 / 3.19
2660	1296 / 0.64	1414 / 0.85	1491 / 1.04	1559 / 1.22	1623 / 1.41	1686 / 1.61	1747 / 1.81	1807 / 2.02	1869 / 2.25	1930 / 2.48	1993 / 2.72	2054 / 2.98	2114 / 3.23	2177 / 3.51
2950	1437 / 0.87	1550 / 1.11	1624 / 1.32	1688 / 1.52	1748 / 1.73	1804 / 1.94	1860 / 2.15	1916 / 2.38	1971 / 2.61	2026 / 2.85	2082 / 3.10	2136 / 3.36	2192 / 3.63	
3240	1578 / 1.15	1687 / 1.43	1757 / 1.66	1818 / 1.88	1875 / 2.11	1929 / 2.33	1980 / 2.56	2031 / 2.80	2082 / 3.04	2133 / 3.30	2182 / 3.55			
3530	1719 / 1.49	1823 / 1.79	1892 / 2.05	1950 / 2.30	2005 / 2.54	2055 / 2.78	2104 / 3.03	2152 / 3.29	2199 / 3.54					
3820	1861 / 1.88	1961 / 2.23	2028 / 2.51	2084 / 2.77	2135 / 3.04	2184 / 3.30								
4110	2002 / 2.34	2098 / 2.72	2163 / 3.03											
4400	2143 / 2.88													

Max Sizeable RPM = 2200 RPM. Table shown extended beyond this point for reference only.

Motor 00158ET3H145T-W22 has an rpm range of 900 to 1750.

Motor 00158OT3H145T-S has an rpm range of 900 to 1750.

Motor 00218ET3H145T-W22 has an rpm range of 900 to 1750.

Motor 00218OT3H145T-S has an rpm range of 900 to 1750.

Motor 00318ET3H182T-W22 has an rpm range of 900 to 1750.

Motor 00318OT3H182T-S has an rpm range of 900 to 1750.

Motor 00536OT3H182T-S has an rpm range of 900 to 2200.

Motor BMN145-2.0I2-CS-UB1-50 (1200RPM) has an rpm range of 900 to 1200.

Motor BMN145-2.0I2-CS-UB1-60 (1200RPM) has an rpm range of 900 to 1200.

Motor BMN145-2.0I2-ES-UB1-50 (1800RPM) has an rpm range of 900 to 1800.

Motor BMN145-2.0I2-ES-UB1-60 (1800RPM) has an rpm range of 900 to 1800.

Motor DTP0022 has an rpm range of 900 to 2200.

Motor DTP0024 has an rpm range of 900 to 1740.

Motor DTP0024-50HZ has an rpm range of 900 to 1415.

Motor DTP0032 has an rpm range of 900 to 2200.

Motor DTP0054 has an rpm range of 900 to 1750.

Motor DTP0054-50 has an rpm range of 900 to 1435.

Motor DTP1/54 has an rpm range of 900 to 1750.

Motor DTP1/54-50HZ has an rpm range of 900 to 1426.

Motor GP0024 has an rpm range of 900 to 1740.

Motor GP0024-50 has an rpm range of 900 to 1440.

Motor GP1/54 has an rpm range of 900 to 1800.

Motor GP1/54-50 has an rpm range of 900 to 1440.

Motor NP0024 has an rpm range of 900 to 1740.