

**RTU2-I.150-15-FA**

CFM	Static Pressure in Inches W.G.															
	0.000	0.250	0.500	0.750	1.000	1.250	1.500	1.750	2.000	2.250	2.500	2.750	3.000	3.250	3.500	3.750
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
750				1007 / 0.29	1150 / 0.42	1276 / 0.55	1389 / 0.70	1494 / 0.85	1592 / 1.01	1685 / 1.18	1773 / 1.36	1856 / 1.54	1933 / 1.72	2011 / 1.91	2089 / 2.12	2161 / 2.33
1075				1039 / 0.36	1180 / 0.51	1308 / 0.66	1424 / 0.83	1531 / 1.01	1629 / 1.19	1720 / 1.38	1807 / 1.57	1889 / 1.78	1965 / 1.98	2044 / 2.20	2116 / 2.42	2185 / 2.64
1400			991 / 0.34	1108 / 0.47	1226 / 0.62	1342 / 0.78	1454 / 0.97	1559 / 1.16	1659 / 1.37	1752 / 1.58	1840 / 1.80	1923 / 2.02	2003 / 2.25	2080 / 2.49	2151 / 2.73	
1725	916 / 0.23	1031 / 0.36	1125 / 0.48	1217 / 0.62	1312 / 0.78	1407 / 0.95	1503 / 1.14	1599 / 1.34	1691 / 1.56	1782 / 1.79	1869 / 2.02	1951 / 2.26	2032 / 2.52	2109 / 2.78	2184 / 3.04	
2050	1088 / 0.39	1190 / 0.54	1273 / 0.68	1350 / 0.84	1429 / 1.00	1507 / 1.18	1587 / 1.37	1667 / 1.58	1748 / 1.80	1829 / 2.03	1909 / 2.28	1986 / 2.53	2064 / 2.80	2140 / 3.08		
2375	1260 / 0.61	1353 / 0.78	1427 / 0.95	1496 / 1.12	1564 / 1.30	1629 / 1.48	1698 / 1.69	1766 / 1.90	1834 / 2.12	1903 / 2.36	1974 / 2.61	2044 / 2.87	2113 / 3.14	2183 / 3.43		
2700	1432 / 0.89	1517 / 1.09	1585 / 1.28	1647 / 1.47	1708 / 1.67	1767 / 1.87	1826 / 2.08	1885 / 2.31	1944 / 2.53	2004 / 2.78	2064 / 3.03	2126 / 3.30	2186 / 3.57			
3025	1605 / 1.25	1682 / 1.48	1746 / 1.69	1804 / 1.91	1859 / 2.12	1912 / 2.34	1966 / 2.57	2018 / 2.80	2070 / 3.04	2123 / 3.29	2176 / 3.55					
3350	1776 / 1.70	1849 / 1.95	1909 / 2.20	1963 / 2.43	2013 / 2.66	2063 / 2.90	2112 / 3.15	2160 / 3.40								
3675	1949 / 2.24	2016 / 2.52	2073 / 2.79	2123 / 3.05	2172 / 3.31											
4000	2121 / 2.89	2185 / 3.20														

Max Sizeable RPM = 2200 RPM. Table shown extended beyond this point for reference only.

- Motor 00158ET3H145T-W22 has an rpm range of 900 to 1750.
- Motor 00158OT3H145T-S has an rpm range of 900 to 1750.
- Motor 00218ET3H145T-W22 has an rpm range of 900 to 1750.
- Motor 00218OT3H145T-S has an rpm range of 900 to 1750.
- Motor 00318ET3H182T-W22 has an rpm range of 900 to 1750.
- Motor 00318OT3H182T-S has an rpm range of 900 to 1750.
- Motor 00536OT3H182T-S has an rpm range of 900 to 2200.
- Motor BMN145-2.0I2-CS-UB1-50 (1200RPM) has an rpm range of 900 to 1200.
- Motor BMN145-2.0I2-CS-UB1-60 (1200RPM) has an rpm range of 900 to 1200.
- Motor BMN145-2.0I2-ES-UB1-50 (1800RPM) has an rpm range of 900 to 1800.
- Motor BMN145-2.0I2-ES-UB1-60 (1800RPM) has an rpm range of 900 to 1800.
- Motor DTP0022 has an rpm range of 900 to 2200.
- Motor DTP0024 has an rpm range of 900 to 1740.
- Motor DTP0024-50HZ has an rpm range of 900 to 1415.
- Motor DTP0032 has an rpm range of 900 to 2200.
- Motor DTP0054 has an rpm range of 900 to 1750.
- Motor DTP0054-50 has an rpm range of 900 to 1435.
- Motor DTP1/54 has an rpm range of 900 to 1750.
- Motor DTP1/54-50HZ has an rpm range of 900 to 1426.
- Motor GP0024 has an rpm range of 900 to 1740.
- Motor GP0024-50 has an rpm range of 900 to 1440.
- Motor GP1/54 has an rpm range of 900 to 1800.
- Motor GP1/54-50 has an rpm range of 900 to 1440.
- Motor NP0024 has an rpm range of 900 to 1740.