

RTU2-I.200-15-FA

CFM	Static Pressure in Inches W.G.															
	0.000	0.250	0.500	0.750	1.000	1.250	1.500	1.750	2.000	2.250	2.500	2.750	3.000	3.250	3.500	3.750
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
1100				1022 / 0.35	1164 / 0.49	1293 / 0.65	1410 / 0.82	1519 / 1.00	1618 / 1.18	1711 / 1.37	1800 / 1.57	1884 / 1.77	1961 / 1.98	2037 / 2.19	2111 / 2.42	2183 / 2.65
1410			970 / 0.31	1085 / 0.44	1203 / 0.59	1319 / 0.75	1431 / 0.93	1538 / 1.12	1638 / 1.33	1732 / 1.54	1822 / 1.76	1905 / 1.98	1986 / 2.21	2064 / 2.45	2136 / 2.68	
1720		995 / 0.31	1092 / 0.44	1185 / 0.57	1280 / 0.72	1376 / 0.89	1473 / 1.07	1568 / 1.27	1662 / 1.49	1752 / 1.70	1840 / 1.94	1922 / 2.17	2005 / 2.43	2082 / 2.68	2158 / 2.95	
2030	1017 / 0.31	1140 / 0.46	1226 / 0.60	1306 / 0.75	1386 / 0.91	1465 / 1.08	1545 / 1.27	1627 / 1.47	1709 / 1.69	1790 / 1.91	1869 / 2.15	1948 / 2.40	2026 / 2.66	2101 / 2.93	2176 / 3.21	
2340	1172 / 0.47	1286 / 0.66	1365 / 0.82	1437 / 0.98	1507 / 1.15	1576 / 1.34	1644 / 1.53	1713 / 1.73	1784 / 1.95	1854 / 2.18	1924 / 2.42	1995 / 2.67	2065 / 2.94	2135 / 3.21		
2650	1327 / 0.69	1435 / 0.90	1508 / 1.08	1575 / 1.27	1637 / 1.45	1699 / 1.65	1758 / 1.85	1820 / 2.07	1881 / 2.29	1941 / 2.52	2003 / 2.77	2065 / 3.02	2129 / 3.29	2190 / 3.57		
2960	1482 / 0.96	1584 / 1.20	1654 / 1.41	1716 / 1.61	1774 / 1.82	1829 / 2.03	1884 / 2.25	1938 / 2.47	1992 / 2.70	2047 / 2.95	2101 / 3.19	2156 / 3.46				
3270	1637 / 1.29	1733 / 1.56	1801 / 1.80	1859 / 2.02	1913 / 2.25	1965 / 2.48	2016 / 2.71	2066 / 2.95	2115 / 3.20	2164 / 3.45						
3580	1793 / 1.69	1883 / 2.00	1949 / 2.26	2004 / 2.51	2056 / 2.76	2105 / 3.00	2151 / 3.25	2198 / 3.51								
3890	1948 / 2.17	2035 / 2.51	2097 / 2.80	2150 / 3.07												
4200	2103 / 2.74	2185 / 3.10														

Max Sizeable RPM = 2200 RPM. Table shown extended beyond this point for reference only.

- Motor 00158ET3H145T-W22 has an rpm range of 900 to 1750.
- Motor 00158OT3H145T-S has an rpm range of 900 to 1750.
- Motor 00218ET3H145T-W22 has an rpm range of 900 to 1750.
- Motor 00218OT3H145T-S has an rpm range of 900 to 1750.
- Motor 00318ET3H182T-W22 has an rpm range of 900 to 1750.
- Motor 00318OT3H182T-S has an rpm range of 900 to 1750.
- Motor 00536OT3H182T-S has an rpm range of 900 to 2200.
- Motor BMN145-2.0I2-CS-UB1-50 (1200RPM) has an rpm range of 900 to 1200.
- Motor BMN145-2.0I2-CS-UB1-60 (1200RPM) has an rpm range of 900 to 1200.
- Motor BMN145-2.0I2-ES-UB1-50 (1800RPM) has an rpm range of 900 to 1800.
- Motor BMN145-2.0I2-ES-UB1-60 (1800RPM) has an rpm range of 900 to 1800.
- Motor DTP0022 has an rpm range of 900 to 2200.
- Motor DTP0024 has an rpm range of 900 to 1740.
- Motor DTP0024-50HZ has an rpm range of 900 to 1415.
- Motor DTP0032 has an rpm range of 900 to 2200.
- Motor DTP0054 has an rpm range of 900 to 1750.
- Motor DTP0054-50 has an rpm range of 900 to 1435.
- Motor DTP1/54 has an rpm range of 900 to 1750.
- Motor DTP1/54-50HZ has an rpm range of 900 to 1426.
- Motor GP0024 has an rpm range of 900 to 1740.
- Motor GP0024-50 has an rpm range of 900 to 1440.
- Motor GP1/54 has an rpm range of 900 to 1800.
- Motor GP1/54-50 has an rpm range of 900 to 1440.
- Motor NP0024 has an rpm range of 900 to 1740.