

**RTU2-I.200HE-15-FA**

CFM	Static Pressure in Inches W.G.															
	0.000	0.250	0.500	0.750	1.000	1.250	1.500	1.750	2.000	2.250	2.500	2.750	3.000	3.250	3.500	3.750
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
1100				1034 / 0.36	1175 / 0.51	1303 / 0.66	1419 / 0.83	1526 / 1.01	1625 / 1.19	1719 / 1.38	1806 / 1.58	1887 / 1.78	1968 / 2.00	2018 / 2.14	2115 / 2.43	2187 / 2.66
1400			980 / 0.32	1096 / 0.45	1215 / 0.60	1332 / 0.77	1443 / 0.95	1549 / 1.14	1649 / 1.35	1743 / 1.56	1830 / 1.77	1915 / 2.00	1994 / 2.23	2071 / 2.46	2144 / 2.70	
1700		1005 / 0.33	1101 / 0.45	1195 / 0.59	1291 / 0.74	1388 / 0.91	1485 / 1.10	1581 / 1.30	1677 / 1.51	1767 / 1.74	1854 / 1.97	1938 / 2.21	2019 / 2.46	2096 / 2.72	2171 / 2.98	
2000	1039 / 0.33	1149 / 0.48	1233 / 0.62	1314 / 0.77	1394 / 0.93	1475 / 1.11	1556 / 1.29	1639 / 1.50	1723 / 1.72	1805 / 1.95	1885 / 2.19	1967 / 2.45	2043 / 2.70	2119 / 2.97	2193 / 3.25	
2300	1195 / 0.51	1295 / 0.68	1372 / 0.84	1444 / 1.00	1511 / 1.17	1583 / 1.36	1652 / 1.56	1723 / 1.76	1794 / 1.98	1862 / 2.20	1939 / 2.46	2010 / 2.72	2081 / 2.98	2154 / 3.27		
2600	1351 / 0.73	1443 / 0.93	1514 / 1.11	1580 / 1.29	1642 / 1.48	1704 / 1.68	1765 / 1.88	1827 / 2.10	1888 / 2.32	1952 / 2.56	2014 / 2.81	2078 / 3.07	2142 / 3.34			
2900	1506 / 1.02	1592 / 1.24	1659 / 1.44	1719 / 1.64	1777 / 1.85	1833 / 2.06	1888 / 2.28	1944 / 2.51	1999 / 2.74	2054 / 2.98	2109 / 3.24	2166 / 3.50				
3200	1662 / 1.37	1742 / 1.62	1806 / 1.85	1863 / 2.07	1916 / 2.29	1967 / 2.51	2018 / 2.75	2069 / 2.99	2118 / 3.23	2167 / 3.48						
3500	1818 / 1.79	1893 / 2.07	1953 / 2.32	2007 / 2.56	2058 / 2.80	2106 / 3.05	2153 / 3.30	2198 / 3.55								
3800	1973 / 2.29	2044 / 2.59	2101 / 2.86	2153 / 3.14												
4100	2129 / 2.88	2196 / 3.21														

Max Sizeable RPM = 2200 RPM. Table shown extended beyond this point for reference only.

- Motor 00158ET3H145T-W22 has an rpm range of 900 to 1750.
- Motor 00158OT3H145T-S has an rpm range of 900 to 1750.
- Motor 00218ET3H145T-W22 has an rpm range of 900 to 1750.
- Motor 00218OT3H145T-S has an rpm range of 900 to 1750.
- Motor 00318ET3H182T-W22 has an rpm range of 900 to 1750.
- Motor 00318OT3H182T-S has an rpm range of 900 to 1750.
- Motor 00536OT3H182T-S has an rpm range of 900 to 2200.
- Motor BMN145-2.0I2-CS-UB1-50 (1200RPM) has an rpm range of 900 to 1200.
- Motor BMN145-2.0I2-CS-UB1-60 (1200RPM) has an rpm range of 900 to 1200.
- Motor BMN145-2.0I2-ES-UB1-50 (1800RPM) has an rpm range of 900 to 1800.
- Motor BMN145-2.0I2-ES-UB1-60 (1800RPM) has an rpm range of 900 to 1800.
- Motor DTP0022 has an rpm range of 900 to 2200.
- Motor DTP0024 has an rpm range of 900 to 1740.
- Motor DTP0024-50HZ has an rpm range of 900 to 1415.
- Motor DTP0032 has an rpm range of 900 to 2200.
- Motor DTP0054 has an rpm range of 900 to 1750.
- Motor DTP0054-50 has an rpm range of 900 to 1435.
- Motor DTP1/54 has an rpm range of 900 to 1750.
- Motor DTP1/54-50HZ has an rpm range of 900 to 1426.
- Motor GP0024 has an rpm range of 900 to 1740.
- Motor GP0024-50 has an rpm range of 900 to 1440.
- Motor GP1/54 has an rpm range of 900 to 1800.
- Motor GP1/54-50 has an rpm range of 900 to 1440.
- Motor NP0024 has an rpm range of 900 to 1740.