

RTU2-I.50-15-FA

CFM	Static Pressure in Inches W.G.															
	0.000	0.250	0.500	0.750	1.000	1.250	1.500	1.750	2.000	2.250	2.500	2.750	3.000	3.250	3.500	3.750
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
500																
730			923 / 0.23	1078 / 0.35	1213 / 0.48	1332 / 0.62	1443 / 0.77	1543 / 0.93	1640 / 1.09	1730 / 1.26	1816 / 1.44	1896 / 1.62	1978 / 1.82	2051 / 2.01	2122 / 2.20	2192 / 2.40
960			1005 / 0.32	1152 / 0.46	1282 / 0.60	1397 / 0.76	1505 / 0.93	1603 / 1.10	1696 / 1.29	1781 / 1.47	1864 / 1.67	1947 / 1.88	2021 / 2.08	2096 / 2.30	2167 / 2.52	
1190		961 / 0.30	1103 / 0.44	1237 / 0.60	1360 / 0.76	1471 / 0.94	1574 / 1.12	1669 / 1.31	1760 / 1.51	1845 / 1.72	1926 / 1.93	2003 / 2.15	2080 / 2.38	2148 / 2.60		
1420	994 / 0.34	1098 / 0.46	1215 / 0.60	1333 / 0.78	1446 / 0.96	1552 / 1.15	1651 / 1.36	1744 / 1.57	1832 / 1.78	1916 / 2.01	1994 / 2.23	2073 / 2.48	2145 / 2.72			
1650	1154 / 0.52	1242 / 0.66	1340 / 0.82	1442 / 1.01	1545 / 1.21	1643 / 1.42	1737 / 1.64	1825 / 1.87	1910 / 2.10	1993 / 2.35	2070 / 2.60	2143 / 2.84				
1880	1315 / 0.78	1392 / 0.93	1475 / 1.10	1563 / 1.30	1653 / 1.51	1742 / 1.74	1831 / 1.98	1914 / 2.23	1996 / 2.48	2073 / 2.74	2149 / 3.01					
2110	1476 / 1.10	1542 / 1.26	1616 / 1.45	1692 / 1.66	1772 / 1.88	1853 / 2.13	1932 / 2.38	2011 / 2.65	2087 / 2.92	2162 / 3.20						
2340	1636 / 1.50	1697 / 1.68	1761 / 1.88	1830 / 2.10	1899 / 2.34	1971 / 2.59	2044 / 2.86	2116 / 3.14	2187 / 3.43							
2570	1797 / 1.98	1852 / 2.18	1909 / 2.39	1969 / 2.63	2033 / 2.88	2098 / 3.15	2163 / 3.43									
2800	1958 / 2.56	2004 / 2.76	2060 / 3.01	2115 / 3.25	2171 / 3.51											

Max Sizeable RPM = 2200 RPM. Table shown extended beyond this point for reference only.

- Motor 00158ET3H145T-W22 has an rpm range of 900 to 1750.
- Motor 00158OT3H145T-S has an rpm range of 900 to 1750.
- Motor 00218ET3H145T-W22 has an rpm range of 900 to 1750.
- Motor 00218OT3H145T-S has an rpm range of 900 to 1750.
- Motor 00318ET3H182T-W22 has an rpm range of 900 to 1750.
- Motor 00318OT3H182T-S has an rpm range of 900 to 1750.
- Motor 00536OT3H182T-S has an rpm range of 900 to 2200.
- Motor BMN145-2.0I2-CS-UB1-50 (1200RPM) has an rpm range of 900 to 1200.
- Motor BMN145-2.0I2-CS-UB1-60 (1200RPM) has an rpm range of 900 to 1200.
- Motor BMN145-2.0I2-ES-UB1-50 (1800RPM) has an rpm range of 900 to 1800.
- Motor BMN145-2.0I2-ES-UB1-60 (1800RPM) has an rpm range of 900 to 1800.
- Motor DTP0022 has an rpm range of 900 to 2200.
- Motor DTP0024 has an rpm range of 900 to 1740.
- Motor DTP0024-50HZ has an rpm range of 900 to 1415.
- Motor DTP0032 has an rpm range of 900 to 2200.
- Motor DTP0054 has an rpm range of 900 to 1750.
- Motor DTP0054-50 has an rpm range of 900 to 1435.
- Motor DTP1/54 has an rpm range of 900 to 1750.
- Motor DTP1/54-50HZ has an rpm range of 900 to 1426.
- Motor GP0024 has an rpm range of 900 to 1740.
- Motor GP0024-50 has an rpm range of 900 to 1440.
- Motor GP1/54 has an rpm range of 900 to 1800.
- Motor GP1/54-50 has an rpm range of 900 to 1440.
- Motor NP0024 has an rpm range of 900 to 1740.