

RTU3-18-FA

CFM	Static Pressure in Inches W.G.															
	0.000	0.250	0.500	0.750	1.000	1.250	1.500	1.750	2.000	2.250	2.500	2.750	3.000	3.250	3.500	3.750
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
1000					929 / 0.50	1035 / 0.66	1133 / 0.82	1221 / 1.00	1302 / 1.17	1381 / 1.37	1453 / 1.56	1522 / 1.76	1587 / 1.97	1653 / 2.20	1712 / 2.42	1770 / 2.65
1500					954 / 0.64	1054 / 0.83	1148 / 1.04	1235 / 1.25	1316 / 1.46	1394 / 1.69	1466 / 1.92	1537 / 2.16	1603 / 2.39	1667 / 2.64	1728 / 2.90	1788 / 3.16
2000				917 / 0.60	1010 / 0.80	1098 / 1.02	1183 / 1.25	1263 / 1.49	1340 / 1.74	1413 / 2.00	1485 / 2.27	1553 / 2.55	1618 / 2.83	1681 / 3.11	1742 / 3.41	1800 / 3.70
2500			929 / 0.62	1013 / 0.81	1093 / 1.03	1169 / 1.25	1244 / 1.50	1316 / 1.76	1386 / 2.04	1453 / 2.33	1519 / 2.62	1582 / 2.93	1645 / 3.24	1705 / 3.56	1763 / 3.89	1821 / 4.22
3000		972 / 0.69	1050 / 0.89	1123 / 1.10	1193 / 1.33	1261 / 1.57	1327 / 1.84	1391 / 2.11	1453 / 2.40	1514 / 2.70	1574 / 3.02	1633 / 3.35	1690 / 3.69	1746 / 4.03	1801 / 4.38	1855 / 4.75
3500	1033 / 0.78	1109 / 1.02	1178 / 1.25	1243 / 1.48	1305 / 1.73	1366 / 1.99	1425 / 2.27	1482 / 2.56	1538 / 2.86	1594 / 3.18	1648 / 3.51	1702 / 3.85	1754 / 4.20	1806 / 4.57	1857 / 4.95	
4000	1181 / 1.16	1248 / 1.43	1310 / 1.70	1369 / 1.97	1426 / 2.24	1480 / 2.52	1533 / 2.81	1585 / 3.12	1637 / 3.44	1687 / 3.77	1736 / 4.11	1785 / 4.47	1833 / 4.84			
4500	1329 / 1.65	1389 / 1.96	1445 / 2.26	1499 / 2.56	1550 / 2.86	1600 / 3.17	1649 / 3.48	1697 / 3.81	1744 / 4.14	1790 / 4.49	1835 / 4.85					
5000	1476 / 2.26	1531 / 2.61	1582 / 2.95	1632 / 3.28	1680 / 3.61	1725 / 3.94	1771 / 4.29	1815 / 4.63	1858 / 4.99							
5500	1624 / 3.01	1674 / 3.40	1721 / 3.77	1767 / 4.14	1811 / 4.50	1854 / 4.86										
6000	1771 / 3.91	1817 / 4.33	1862 / 4.74													

Max Sizeable RPM = 1900 RPM. Table shown extended beyond this point for reference only.

- Motor 00218ET3H145T-W22 has an rpm range of 900 to 1750.
- Motor 00218OT3H145T-S has an rpm range of 900 to 1750.
- Motor 00312ET3H213T-S has an rpm range of 900 to 1150.
- Motor 00318ET3H182T-W22 has an rpm range of 900 to 1750.
- Motor 00318OT3H182T-S has an rpm range of 900 to 1750.
- Motor 00518ET3H184T-W22 has an rpm range of 900 to 1750.
- Motor 00518OT3H184T-S has an rpm range of 900 to 1750.
- Motor BMN145-2.0I2-CS-UB1-50 (1200RPM) has an rpm range of 900 to 1200.
- Motor BMN145-2.0I2-CS-UB1-60 (1200RPM) has an rpm range of 900 to 1200.
- Motor BMN145-2.0I2-ES-UB1-50 (1800RPM) has an rpm range of 900 to 1800.
- Motor BMN145-2.0I2-ES-UB1-60 (1800RPM) has an rpm range of 900 to 1800.
- Motor DHP0026 has an rpm range of 900 to 1150.
- Motor DTP0024 has an rpm range of 900 to 1740.
- Motor DTP0024-50HZ has an rpm range of 900 to 1415.
- Motor DTP0026 has an rpm range of 900 to 1150.
- Motor DTP0034 has an rpm range of 900 to 1755.
- Motor DTP0034-50HZ has an rpm range of 900 to 1438.
- Motor DTP0054 has an rpm range of 900 to 1750.
- Motor DTP0054-50 has an rpm range of 900 to 1435.
- Motor GP0024 has an rpm range of 900 to 1740.
- Motor GP0024-50 has an rpm range of 900 to 1440.
- Motor GP0026 has an rpm range of 900 to 1150.
- Motor GP0034 has an rpm range of 900 to 1800.
- Motor GP0034-50 has an rpm range of 900 to 1440.
- Motor GP0054 has an rpm range of 900 to 1800.
- Motor GP0054-50 has an rpm range of 900 to 1440.
- Motor NP0024 has an rpm range of 900 to 1740.
- Motor NP0026 has an rpm range of 900 to 1150.
- Motor NP0054 has an rpm range of 900 to 1745.