

RTU3-20-FA

CFM	Static Pressure in Inches W.G.								
	0.000	0.500	1.000	1.500	2.000	2.500	3.000	3.500	4.000
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
1000				1041 / 0.90	1195 / 1.32	1328 / 1.77	1445 / 2.26		
1600				1046 / 1.12	1208 / 1.61	1350 / 2.13	1477 / 2.69	1594 / 3.29	1699 / 3.90
2200				1058 / 1.34	1211 / 1.89	1351 / 2.49	1479 / 3.13	1599 / 3.80	
2800			956 / 1.08	1101 / 1.61	1237 / 2.21	1365 / 2.86	1485 / 3.56	1600 / 4.29	
3400			1037 / 1.38	1167 / 1.96	1288 / 2.60	1403 / 3.30	1512 / 4.04	1618 / 4.82	
4000		991 / 1.18	1127 / 1.76	1246 / 2.40	1357 / 3.09	1461 / 3.82	1561 / 4.61	1658 / 5.43	
4600	952 / 0.94	1096 / 1.58	1223 / 2.24	1334 / 2.94	1437 / 3.68	1533 / 4.46	1625 / 5.29		
5200	1076 / 1.36	1205 / 2.08	1322 / 2.81	1427 / 3.58	1524 / 4.38	1614 / 5.21			
5800	1200 / 1.89	1316 / 2.68	1426 / 3.50	1525 / 4.34	1616 / 5.20				
6400	1324 / 2.53	1430 / 3.41	1531 / 4.31	1625 / 5.22					
7000	1448 / 3.32	1545 / 4.27	1640 / 5.26						

Max Sizeable RPM = 1700 RPM. Table shown extended beyond this point for reference only.

Motor 00312ET3H213T-S has an rpm range of 900 to 1150.

Motor 00318ET3H182T-W22 has an rpm range of 900 to 1700.

Motor 00318OT3H182T-S has an rpm range of 900 to 1700.

Motor 00512ET3H215T-W22 has an rpm range of 900 to 1150.

Motor 00512OT3H215T-S has an rpm range of 900 to 1150.

Motor 00518ET3H184T-W22 has an rpm range of 900 to 1700.

Motor 00518OT3H184T-S has an rpm range of 900 to 1700.

Motor 00718ET3H213T-W22 has an rpm range of 900 to 1700.

Motor 00718OT3H213T-S has an rpm range of 900 to 1700.

Motor DHP0056 has an rpm range of 900 to 1165.

Motor DTP0034 has an rpm range of 900 to 1700.

Motor DTP0034-50HZ has an rpm range of 900 to 1438.

Motor DTP0036 has an rpm range of 900 to 1150.

Motor DTP0054 has an rpm range of 900 to 1700.

Motor DTP0054-50 has an rpm range of 900 to 1435.

Motor DTP0056 has an rpm range of 900 to 1150.

Motor DTP7/54 has an rpm range of 900 to 1700.

Motor DTP7/54-50 has an rpm range of 900 to 1470.

Motor GP0034 has an rpm range of 900 to 1700.

Motor GP0034-50 has an rpm range of 900 to 1440.

Motor GP0036 has an rpm range of 900 to 1150.

Motor GP0054 has an rpm range of 900 to 1700.

Motor GP0054-50 has an rpm range of 900 to 1440.

Motor GP0056 has an rpm range of 900 to 1150.

Motor GP7/54 has an rpm range of 900 to 1700.

Motor GP7/54-50 has an rpm range of 900 to 1440.

Motor NP0056 has an rpm range of 900 to 1150.