

RTU3-E.152-18-FA

CFM	Static Pressure in Inches W.G.															
	0.000	0.250	0.500	0.750	1.000	1.250	1.500	1.750	2.000	2.250	2.500	2.750	3.000	3.250	3.500	3.750
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
1000					936 / 0.51	1043 / 0.66	1139 / 0.83	1227 / 1.00	1311 / 1.18	1387 / 1.36	1460 / 1.56	1529 / 1.76	1595 / 1.97	1658 / 2.19	1718 / 2.41	1776 / 2.64
1450					963 / 0.65	1064 / 0.84	1156 / 1.04	1244 / 1.25	1325 / 1.46	1402 / 1.68	1475 / 1.91	1546 / 2.14	1611 / 2.37	1676 / 2.62	1737 / 2.86	1797 / 3.11
1900				913 / 0.59	1017 / 0.81	1107 / 1.03	1192 / 1.26	1273 / 1.50	1350 / 1.75	1424 / 2.01	1495 / 2.27	1562 / 2.53	1628 / 2.81	1692 / 3.09	1753 / 3.37	1811 / 3.65
2350			925 / 0.62	1012 / 0.81	1094 / 1.02	1173 / 1.26	1249 / 1.50	1322 / 1.77	1394 / 2.04	1462 / 2.33	1529 / 2.62	1593 / 2.93	1655 / 3.23	1715 / 3.54	1775 / 3.87	1832 / 4.19
2800		959 / 0.68	1039 / 0.88	1114 / 1.08	1187 / 1.31	1257 / 1.55	1325 / 1.82	1391 / 2.09	1455 / 2.38	1518 / 2.69	1579 / 3.01	1639 / 3.33	1698 / 3.67	1754 / 4.01	1810 / 4.36	1865 / 4.73
3250	1017 / 0.76	1089 / 0.99	1159 / 1.21	1225 / 1.44	1290 / 1.68	1354 / 1.94	1415 / 2.22	1475 / 2.51	1533 / 2.81	1591 / 3.13	1646 / 3.46	1702 / 3.81	1756 / 4.16	1809 / 4.53	1860 / 4.90	
3700	1157 / 1.12	1221 / 1.38	1283 / 1.63	1343 / 1.89	1402 / 2.16	1458 / 2.43	1515 / 2.72	1569 / 3.03	1623 / 3.35	1675 / 3.68	1727 / 4.02	1777 / 4.38	1825 / 4.73			
4150	1298 / 1.59	1355 / 1.88	1411 / 2.16	1465 / 2.45	1518 / 2.73	1571 / 3.03	1622 / 3.34	1671 / 3.66	1721 / 3.99	1769 / 4.34	1817 / 4.70					
4600	1438 / 2.16	1490 / 2.48	1541 / 2.80	1591 / 3.11	1639 / 3.43	1687 / 3.75	1734 / 4.08	1780 / 4.42	1826 / 4.77							
5050	1579 / 2.85	1626 / 3.21	1673 / 3.56	1719 / 3.91	1763 / 4.25	1807 / 4.60	1851 / 4.96									
5500	1720 / 3.69	1763 / 4.08	1806 / 4.46	1848 / 4.84												

Max Sizeable RPM = 1900 RPM. Table shown extended beyond this point for reference only.

- Motor 00218ET3H145T-W22 has an rpm range of 900 to 1750.
- Motor 00218OT3H145T-S has an rpm range of 900 to 1750.
- Motor 00312ET3H213T-S has an rpm range of 900 to 1150.
- Motor 00318ET3H182T-W22 has an rpm range of 900 to 1750.
- Motor 00318OT3H182T-S has an rpm range of 900 to 1750.
- Motor 00518ET3H184T-W22 has an rpm range of 900 to 1750.
- Motor 00518OT3H184T-S has an rpm range of 900 to 1750.
- Motor BMN145-2.0I2-CS-UB1-50 (1200RPM) has an rpm range of 900 to 1200.
- Motor BMN145-2.0I2-CS-UB1-60 (1200RPM) has an rpm range of 900 to 1200.
- Motor BMN145-2.0I2-ES-UB1-50 (1800RPM) has an rpm range of 900 to 1800.
- Motor BMN145-2.0I2-ES-UB1-60 (1800RPM) has an rpm range of 900 to 1800.
- Motor DHP0026 has an rpm range of 900 to 1150.
- Motor DTP0024 has an rpm range of 900 to 1740.
- Motor DTP0024-50HZ has an rpm range of 900 to 1415.
- Motor DTP0026 has an rpm range of 900 to 1150.
- Motor DTP0034 has an rpm range of 900 to 1755.
- Motor DTP0034-50HZ has an rpm range of 900 to 1438.
- Motor DTP0054 has an rpm range of 900 to 1750.
- Motor DTP0054-50 has an rpm range of 900 to 1435.
- Motor GP0024 has an rpm range of 900 to 1740.
- Motor GP0024-50 has an rpm range of 900 to 1440.
- Motor GP0026 has an rpm range of 900 to 1150.
- Motor GP0034 has an rpm range of 900 to 1800.
- Motor GP0034-50 has an rpm range of 900 to 1440.
- Motor GP0054 has an rpm range of 900 to 1800.
- Motor GP0054-50 has an rpm range of 900 to 1440.
- Motor NP0024 has an rpm range of 900 to 1740.
- Motor NP0026 has an rpm range of 900 to 1150.
- Motor NP0054 has an rpm range of 900 to 1745.