

RTU3-E.154-18-FA

CFM	Static Pressure in Inches W.G.															
	0.000	0.250	0.500	0.750	1.000	1.250	1.500	1.750	2.000	2.250	2.500	2.750	3.000	3.250	3.500	3.750
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
1000					936 / 0.51	1043 / 0.66	1139 / 0.83	1227 / 1.00	1311 / 1.18	1387 / 1.36	1460 / 1.56	1529 / 1.76	1595 / 1.97	1658 / 2.19	1718 / 2.41	1776 / 2.64
1460					964 / 0.65	1063 / 0.85	1157 / 1.05	1244 / 1.25	1326 / 1.47	1402 / 1.69	1475 / 1.91	1545 / 2.14	1611 / 2.38	1676 / 2.62	1738 / 2.87	1798 / 3.13
1920				926 / 0.62	1020 / 0.82	1109 / 1.04	1194 / 1.27	1275 / 1.51	1351 / 1.76	1425 / 2.02	1495 / 2.28	1564 / 2.55	1628 / 2.82	1692 / 3.10	1753 / 3.39	1811 / 3.67
2380			932 / 0.63	1018 / 0.83	1100 / 1.04	1178 / 1.27	1254 / 1.52	1327 / 1.79	1398 / 2.06	1466 / 2.35	1532 / 2.65	1595 / 2.95	1657 / 3.26	1718 / 3.58	1776 / 3.90	1834 / 4.22
2840		971 / 0.70	1049 / 0.90	1123 / 1.11	1196 / 1.34	1265 / 1.58	1333 / 1.85	1398 / 2.13	1462 / 2.42	1524 / 2.73	1585 / 3.04	1644 / 3.37	1703 / 3.71	1759 / 4.05	1815 / 4.41	1868 / 4.77
3300	1032 / 0.80	1103 / 1.03	1172 / 1.25	1238 / 1.49	1302 / 1.73	1365 / 1.99	1425 / 2.27	1484 / 2.56	1543 / 2.87	1600 / 3.19	1655 / 3.52	1710 / 3.87	1763 / 4.22	1815 / 4.59	1868 / 4.97	
3760	1176 / 1.18	1239 / 1.44	1300 / 1.70	1359 / 1.96	1417 / 2.23	1473 / 2.51	1528 / 2.80	1582 / 3.11	1635 / 3.43	1687 / 3.76	1738 / 4.11	1789 / 4.47	1838 / 4.83			
4220	1320 / 1.67	1376 / 1.96	1431 / 2.25	1485 / 2.54	1537 / 2.83	1588 / 3.14	1639 / 3.45	1688 / 3.77	1737 / 4.11	1784 / 4.45	1832 / 4.81					
4680	1463 / 2.27	1515 / 2.60	1564 / 2.92	1613 / 3.24	1661 / 3.57	1709 / 3.90	1755 / 4.23	1800 / 4.57	1845 / 4.93							
5140	1607 / 3.01	1654 / 3.37	1700 / 3.73	1744 / 4.08	1788 / 4.43	1832 / 4.79										
5600	1751 / 3.89	1794 / 4.29	1836 / 4.68													

Max Sizeable RPM = 1900 RPM. Table shown extended beyond this point for reference only.

- Motor 00218ET3H145T-W22 has an rpm range of 900 to 1750.
- Motor 00218OT3H145T-S has an rpm range of 900 to 1750.
- Motor 00312ET3H213T-S has an rpm range of 900 to 1150.
- Motor 00318ET3H182T-W22 has an rpm range of 900 to 1750.
- Motor 00318OT3H182T-S has an rpm range of 900 to 1750.
- Motor 00518ET3H184T-W22 has an rpm range of 900 to 1750.
- Motor 00518OT3H184T-S has an rpm range of 900 to 1750.
- Motor BMN145-2.0I2-CS-UB1-50 (1200RPM) has an rpm range of 900 to 1200.
- Motor BMN145-2.0I2-CS-UB1-60 (1200RPM) has an rpm range of 900 to 1200.
- Motor BMN145-2.0I2-ES-UB1-50 (1800RPM) has an rpm range of 900 to 1800.
- Motor BMN145-2.0I2-ES-UB1-60 (1800RPM) has an rpm range of 900 to 1800.
- Motor DHP0026 has an rpm range of 900 to 1150.
- Motor DTP0024 has an rpm range of 900 to 1740.
- Motor DTP0024-50HZ has an rpm range of 900 to 1415.
- Motor DTP0026 has an rpm range of 900 to 1150.
- Motor DTP0034 has an rpm range of 900 to 1755.
- Motor DTP0034-50HZ has an rpm range of 900 to 1438.
- Motor DTP0054 has an rpm range of 900 to 1750.
- Motor DTP0054-50 has an rpm range of 900 to 1435.
- Motor GP0024 has an rpm range of 900 to 1740.
- Motor GP0024-50 has an rpm range of 900 to 1440.
- Motor GP0026 has an rpm range of 900 to 1150.
- Motor GP0034 has an rpm range of 900 to 1800.
- Motor GP0034-50 has an rpm range of 900 to 1440.
- Motor GP0054 has an rpm range of 900 to 1800.
- Motor GP0054-50 has an rpm range of 900 to 1440.
- Motor NP0024 has an rpm range of 900 to 1740.
- Motor NP0026 has an rpm range of 900 to 1150.
- Motor NP0054 has an rpm range of 900 to 1745.