

RTU3-E.602-20-FA

CFM	Static Pressure in Inches W.G.								
	0.000	0.500	1.000	1.500	2.000	2.500	3.000	3.500	4.000
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
1900				1071 / 1.29	1224 / 1.81	1360 / 2.37	1483 / 2.96	1597 / 3.58	1701 / 4.22
2410			939 / 1.00	1101 / 1.54	1247 / 2.12	1380 / 2.74	1502 / 3.40	1615 / 4.09	1720 / 4.80
2920			1006 / 1.26	1148 / 1.83	1282 / 2.46	1409 / 3.15	1526 / 3.87	1637 / 4.62	1741 / 5.40
3430		953 / 1.06	1086 / 1.60	1211 / 2.20	1332 / 2.87	1448 / 3.60	1559 / 4.37	1665 / 5.18	1765 / 6.02
3940		1055 / 1.43	1175 / 2.02	1287 / 2.66	1392 / 3.34	1502 / 4.13	1604 / 4.94	1703 / 5.80	1799 / 6.71
4450	1009 / 1.22	1159 / 1.89	1270 / 2.53	1372 / 3.22	1471 / 3.96	1567 / 4.76	1660 / 5.61	1753 / 6.51	
4960	1125 / 1.69	1265 / 2.44	1369 / 3.15	1464 / 3.89	1554 / 4.68	1642 / 5.51	1728 / 6.40		
5470	1241 / 2.26	1373 / 3.11	1471 / 3.88	1559 / 4.68	1643 / 5.51	1724 / 6.39			
5980	1356 / 2.96	1481 / 3.89	1575 / 4.74	1658 / 5.60	1737 / 6.49				
6490	1472 / 3.78	1591 / 4.81	1680 / 5.74	1759 / 6.66					
7000	1588 / 4.74	1677 / 5.61	1786 / 6.87						

Max Sizeable RPM = 1800 RPM. Table shown extended beyond this point for reference only.

Motor 00312ET3H213T-S has an rpm range of 900 to 1150.

Motor 00318ET3H182T-W22 has an rpm range of 900 to 1750.

Motor 00318OT3H182T-S has an rpm range of 900 to 1750.

Motor 00512ET3H215T-W22 has an rpm range of 900 to 1150.

Motor 00512OT3H215T-S has an rpm range of 900 to 1150.

Motor 00518ET3H184T-W22 has an rpm range of 900 to 1750.

Motor 00518OT3H184T-S has an rpm range of 900 to 1750.

Motor 00718ET3H213T-W22 has an rpm range of 900 to 1750.

Motor 00718OT3H213T-S has an rpm range of 900 to 1750.

Motor DHP0056 has an rpm range of 900 to 1165.

Motor DTP0034 has an rpm range of 900 to 1755.

Motor DTP0034-50HZ has an rpm range of 900 to 1438.

Motor DTP0036 has an rpm range of 900 to 1150.

Motor DTP0054 has an rpm range of 900 to 1750.

Motor DTP0054-50 has an rpm range of 900 to 1435.

Motor DTP0056 has an rpm range of 900 to 1150.

Motor DTP7/54 has an rpm range of 900 to 1750.

Motor DTP7/54-50 has an rpm range of 900 to 1470.

Motor GP0034 has an rpm range of 900 to 1800.

Motor GP0034-50 has an rpm range of 900 to 1440.

Motor GP0036 has an rpm range of 900 to 1150.

Motor GP0054 has an rpm range of 900 to 1800.

Motor GP0054-50 has an rpm range of 900 to 1440.

Motor GP0056 has an rpm range of 900 to 1150.

Motor GP7/54 has an rpm range of 900 to 1800.

Motor GP7/54-50 has an rpm range of 900 to 1440.

Motor NP0056 has an rpm range of 900 to 1150.