

RTU3-E.904-22-FA

CFM	Static Pressure in Inches W.G.								
	0.000	0.500	1.000	1.500	2.000	2.500	3.000	3.500	4.000
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
3000		939 / 0.56	1080 / 0.92	1216 / 1.33	1346 / 1.77	1471 / 2.24	1586 / 2.73	1696 / 3.25	1800 / 3.78
3400	892 / 0.38	1028 / 0.72	1153 / 1.10	1276 / 1.53	1395 / 2.00	1510 / 2.50	1621 / 3.03	1726 / 3.58	1827 / 4.15
3800	997 / 0.53	1121 / 0.90	1234 / 1.31	1344 / 1.77	1453 / 2.27	1560 / 2.80	1663 / 3.35	1763 / 3.94	1860 / 4.54
4200	1102 / 0.72	1215 / 1.12	1319 / 1.56	1419 / 2.05	1519 / 2.57	1617 / 3.13	1714 / 3.71	1808 / 4.32	
4600	1207 / 0.94	1311 / 1.38	1407 / 1.85	1500 / 2.36	1591 / 2.91	1682 / 3.49	1771 / 4.11	1859 / 4.74	
5000	1312 / 1.21	1409 / 1.68	1498 / 2.19	1584 / 2.73	1669 / 3.30	1753 / 3.91	1836 / 4.55		
5400	1417 / 1.52	1508 / 2.03	1591 / 2.57	1671 / 3.14	1750 / 3.74	1829 / 4.38			
5800	1522 / 1.88	1606 / 2.43	1686 / 3.00	1761 / 3.60	1835 / 4.23				
6200	1627 / 2.30	1707 / 2.88	1781 / 3.49	1852 / 4.12					
6600	1732 / 2.77	1807 / 3.39							
7000	1837 / 3.31								

Max Sizeable RPM = 1870 RPM. Table shown extended beyond this point for reference only.

Motor 186729/A01-ECM-50-480-22 has an rpm range of 800 to 1870.

Motor 186729/A01-ECM-60-480-22 has an rpm range of 800 to 1870.

Motor 186732/A01-ECM-50-240-22 has an rpm range of 800 to 1870.

Motor 186732/A01-ECM-60-240-22 has an rpm range of 800 to 1870.