

RTU3-I.150-18-FA

CFM	Static Pressure in Inches W.G.															
	0.000	0.250	0.500	0.750	1.000	1.250	1.500	1.750	2.000	2.250	2.500	2.750	3.000	3.250	3.500	3.750
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
1000					960 / 0.54	1063 / 0.69	1155 / 0.83	1241 / 0.99	1321 / 1.15	1395 / 1.32	1466 / 1.50	1534 / 1.69	1600 / 1.89	1661 / 2.09	1721 / 2.31	1779 / 2.54
1350					999 / 0.70	1098 / 0.89	1188 / 1.08	1272 / 1.27	1351 / 1.47	1426 / 1.66	1497 / 1.86	1562 / 2.06	1628 / 2.27	1690 / 2.48	1749 / 2.70	1807 / 2.93
1700				952 / 0.66	1049 / 0.86	1142 / 1.09	1228 / 1.32	1311 / 1.56	1388 / 1.80	1460 / 2.04	1530 / 2.28	1596 / 2.52	1660 / 2.76	1721 / 3.00	1780 / 3.25	1838 / 3.50
2050			942 / 0.65	1031 / 0.84	1117 / 1.06	1200 / 1.31	1280 / 1.57	1357 / 1.84	1431 / 2.12	1501 / 2.40	1568 / 2.69	1633 / 2.97	1696 / 3.26	1757 / 3.55	1814 / 3.84	1870 / 4.13
2400		962 / 0.71	1045 / 0.90	1123 / 1.10	1199 / 1.32	1273 / 1.58	1345 / 1.85	1415 / 2.14	1483 / 2.44	1550 / 2.76	1614 / 3.08	1677 / 3.41	1737 / 3.74	1795 / 4.07	1852 / 4.40	
2750	993 / 0.77	1078 / 1.00	1153 / 1.21	1223 / 1.43	1291 / 1.67	1357 / 1.92	1423 / 2.21	1486 / 2.50	1549 / 2.82	1610 / 3.15	1671 / 3.50	1730 / 3.86	1787 / 4.22	1843 / 4.59	1898 / 4.96	
3100	1119 / 1.10	1196 / 1.37	1265 / 1.61	1329 / 1.85	1390 / 2.10	1450 / 2.36	1509 / 2.65	1567 / 2.96	1625 / 3.28	1681 / 3.62	1737 / 3.98	1792 / 4.35	1845 / 4.73			
3450	1245 / 1.51	1316 / 1.82	1379 / 2.09	1438 / 2.35	1494 / 2.62	1549 / 2.90	1604 / 3.20	1657 / 3.51	1710 / 3.84	1761 / 4.19	1813 / 4.56	1864 / 4.94				
3800	1372 / 2.02	1437 / 2.37	1495 / 2.67	1550 / 2.96	1603 / 3.25	1654 / 3.55	1703 / 3.86	1753 / 4.18	1801 / 4.52	1849 / 4.87						
4150	1498 / 2.63	1558 / 3.01	1613 / 3.35	1664 / 3.67	1713 / 3.99	1761 / 4.31	1807 / 4.63	1854 / 4.97								
4500	1625 / 3.36	1680 / 3.77	1731 / 4.15	1780 / 4.50	1826 / 4.85											

Max Sizeable RPM = 1900 RPM. Table shown extended beyond this point for reference only.

- Motor 00218ET3H145T-W22 has an rpm range of 900 to 1750.
- Motor 00218OT3H145T-S has an rpm range of 900 to 1750.
- Motor 00312ET3H213T-S has an rpm range of 900 to 1150.
- Motor 00318ET3H182T-W22 has an rpm range of 900 to 1750.
- Motor 00318OT3H182T-S has an rpm range of 900 to 1750.
- Motor 00518ET3H184T-W22 has an rpm range of 900 to 1750.
- Motor 00518OT3H184T-S has an rpm range of 900 to 1750.
- Motor BMN145-2.0I2-CS-UB1-50 (1200RPM) has an rpm range of 900 to 1200.
- Motor BMN145-2.0I2-CS-UB1-60 (1200RPM) has an rpm range of 900 to 1200.
- Motor BMN145-2.0I2-ES-UB1-50 (1800RPM) has an rpm range of 900 to 1800.
- Motor BMN145-2.0I2-ES-UB1-60 (1800RPM) has an rpm range of 900 to 1800.
- Motor DHP0026 has an rpm range of 900 to 1150.
- Motor DTP0024 has an rpm range of 900 to 1740.
- Motor DTP0024-50HZ has an rpm range of 900 to 1415.
- Motor DTP0026 has an rpm range of 900 to 1150.
- Motor DTP0034 has an rpm range of 900 to 1755.
- Motor DTP0034-50HZ has an rpm range of 900 to 1438.
- Motor DTP0054 has an rpm range of 900 to 1750.
- Motor DTP0054-50 has an rpm range of 900 to 1435.
- Motor GP0024 has an rpm range of 900 to 1740.
- Motor GP0024-50 has an rpm range of 900 to 1440.
- Motor GP0026 has an rpm range of 900 to 1150.
- Motor GP0034 has an rpm range of 900 to 1800.
- Motor GP0034-50 has an rpm range of 900 to 1440.
- Motor GP0054 has an rpm range of 900 to 1800.
- Motor GP0054-50 has an rpm range of 900 to 1440.
- Motor NP0024 has an rpm range of 900 to 1740.
- Motor NP0026 has an rpm range of 900 to 1150.
- Motor NP0054 has an rpm range of 900 to 1745.