

RTU3-I.200-15-FA

CFM	Static Pressure in Inches W.G.														
	0.000	0.250	0.500	0.750	1.000	1.250	1.500	1.750	2.000	2.250	2.500	2.750	3.000	3.250	3.500
	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP	RPM/BHP
1100				1029 / 0.36	1170 / 0.50	1299 / 0.66	1416 / 0.82	1524 / 1.00	1622 / 1.19	1716 / 1.38	1803 / 1.58	1887 / 1.78	1964 / 1.99	2041 / 2.21	2111 / 2.42
1400			974 / 0.32	1090 / 0.45	1209 / 0.59	1326 / 0.76	1437 / 0.94	1544 / 1.13	1643 / 1.33	1737 / 1.54	1828 / 1.77	1910 / 1.98	1991 / 2.22	2068 / 2.45	2141 / 2.69
1700		996 / 0.32	1093 / 0.44	1187 / 0.58	1283 / 0.73	1380 / 0.90	1477 / 1.08	1574 / 1.28	1668 / 1.49	1760 / 1.72	1848 / 1.95	1932 / 2.19	2012 / 2.44	2088 / 2.69	2163 / 2.95
2000	1025 / 0.32	1138 / 0.46	1224 / 0.60	1305 / 0.75	1384 / 0.91	1465 / 1.08	1547 / 1.27	1630 / 1.48	1712 / 1.69	1795 / 1.92	1878 / 2.16	1957 / 2.41	2035 / 2.67	2112 / 2.95	
2300	1178 / 0.48	1283 / 0.66	1361 / 0.82	1433 / 0.98	1502 / 1.15	1572 / 1.33	1642 / 1.52	1713 / 1.73	1784 / 1.95	1856 / 2.18	1928 / 2.42	2000 / 2.68	2072 / 2.95		
2600	1332 / 0.70	1429 / 0.90	1501 / 1.08	1567 / 1.26	1630 / 1.45	1692 / 1.64	1753 / 1.84	1814 / 2.05	1877 / 2.28	1939 / 2.51	2003 / 2.76				
2900	1486 / 0.97	1576 / 1.20	1644 / 1.40	1706 / 1.60	1763 / 1.80	1819 / 2.01	1875 / 2.23	1929 / 2.45	1985 / 2.68	2041 / 2.93					
3200	1639 / 1.30	1724 / 1.56	1789 / 1.78	1847 / 2.00	1900 / 2.22	1952 / 2.45	2004 / 2.68	2054 / 2.92							
3500	1793 / 1.70	1873 / 1.98	1935 / 2.24	1990 / 2.48	2040 / 2.72	2088 / 2.96									
3800	1947 / 2.18	2022 / 2.49	2081 / 2.77												
4100	2100 / 2.74														

Max Sizeable RPM = 2200 RPM. Table shown extended beyond this point for reference only.

Motor 00158ET3H145T-W22 has an rpm range of 900 to 1750.

Motor 00158OT3H145T-S has an rpm range of 900 to 1750.

Motor 00218ET3H145T-W22 has an rpm range of 900 to 1750.

Motor 00218OT3H145T-S has an rpm range of 900 to 1750.

Motor 00318OT3H182T-S has an rpm range of 900 to 1750.

Motor BMN145-2.0I2-CS-UB1-50 (1200RPM) has an rpm range of 900 to 1200.

Motor BMN145-2.0I2-CS-UB1-60 (1200RPM) has an rpm range of 900 to 1200.

Motor BMN145-2.0I2-ES-UB1-50 (1800RPM) has an rpm range of 900 to 1800.

Motor BMN145-2.0I2-ES-UB1-60 (1800RPM) has an rpm range of 900 to 1800.

Motor DTP0024 has an rpm range of 900 to 1740.

Motor DTP0024-50HZ has an rpm range of 900 to 1415.

Motor DTP0032 has an rpm range of 900 to 2200.

Motor DTP0034 has an rpm range of 900 to 1755.

Motor DTP1/54 has an rpm range of 900 to 1750.

Motor DTP1/54-50HZ has an rpm range of 900 to 1426.

Motor GP0024 has an rpm range of 900 to 1740.

Motor GP0024-50 has an rpm range of 900 to 1440.

Motor GP1/54 has an rpm range of 900 to 1800.

Motor GP1/54-50 has an rpm range of 900 to 1440.